



Pulse EP

Modbus Manual

EP2I00/EP200N
EPI000/EP200

Pulse Instruments

Notice

© 2022 Pulse, Primordial Diagnostics Inc. (hereinafter "Pulse")
3233 Mission Oaks Blvd, Camarillo, CA 93012 USA
(800) 462-1926
All Rights Reserved
Printed in USA

Proprietary Material

The information and descriptions contained herein are the property of PULSE. Such information and descriptions may not be copied or reproduced by any means, or disseminated or distributed without the express prior written permission of PULSE, 3233 Mission Oaks Blvd, Camarillo, CA 93012.

This document is for information purposes only and is subject to change without notice.

Statement of Limited Warranty

PULSE warrants equipment of its manufacture, and bearing its identification to be free from defects in workmanship and material for a period of 24 months for electronics and 12 months for mechanical parts and electrodes from date of delivery from the factory or authorized distributor under normal use and service and otherwise when such equipment is used in accordance with instructions furnished by PULSE and for the purposes disclosed in writing at the time of purchase, if any. PULSE's liability under this warranty shall be limited to replacement or repair, F.O.B. Camarillo, CA U.S.A. of any defective equipment or part which, having been returned to PULSE, transportation charges prepaid, has been inspected and determined by PULSE to be defective. Replaceable elastomeric parts and glass components are expendable and are not covered by any warranty.

THIS WARRANTY IS IN LIEU OF ANY OTHER WARRANTY, EITHER EXPRESS OR IMPLIED, AS TO DESCRIPTION, QUALITY, MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR USE, OR ANY OTHER MATTER.

*180676 Rev I
April 2022*

pulseinstruments.net

Table of Contents

1.0	SCOPE	2
2.0	INTRODUCTION	2
3.0	OVERVIEW	2
3.1	MODBUS SETTINGS	3
4.0	MODBUS/TCP DRIVER	3
4.1	MODBUS/TCP PROTOCOL	3
4.1.1	MBAP Header	3
4.1.2	Protocol Data Unit	4
4.1.3	Modbus/TCP Function Codes	4
4.1.3.1	Function Code 1, Read Coils	5
4.1.3.2	Function Code 2, Read Discrete Inputs	5
4.1.3.3	Function Code 3, Read Holding Registers	6
4.1.3.4	Function Code 4, Read Input Registers	6
4.1.3.5	Function Code 5, Write Single Coil	7
4.1.3.6	Function Code 6, Write Single Holding Register	7
4.1.3.7	Function Code 16, Write Multiple Holding Registers	8
4.1.4	Modbus/TCP Exception Error Codes	8
4.2	TCP/IP INTERFACE	9
4.3	DATA REFRESH	9
4.4	DATA ENCODING	9
4.4.1	Coils and Discrete Inputs	9
4.4.1.1	Boolean	9
4.4.2	Holding Register and Input Registers	9
4.4.2.1	16-Bit Word (Boolean)	9
4.4.2.2	16-Bit Word (Bitfield)	10
4.4.2.3	16-Bit Word (Status)	10
4.4.2.4	16-Bit Word (Integer)	10
4.4.2.5	32-Bit Value (Integer)	10
4.4.2.6	32-Bit Value (Float)	10
4.4.2.7	32-Bit Inverse Data Format (Integer or Float)	11

5.0	DATA DICTIONARY	11
5.1	ADDRESSING (0- OR 1-BASED)	11
5.2	ADDRESS MAPS	11
5.2.1	EP200 Controller – I/O Channel Address Maps.....	12
5.2.2	EP1000 Controller – I/O Channel Address Maps.....	13
5.2.3	EP200N Controller – I/O Channel Address Maps	15
5.2.4	EP2100 Controller – I/O Channel Address Maps	16
5.2.5	Alternate Address Maps.....	19
5.3	TYPE-SPECIFIC ADDRESS MAPS.....	20
5.3.1	System Address Map.....	20
5.3.2	Network Address Map.....	21
5.3.3	Sensor Input Address Maps.....	22
5.3.3.1	Sensor Input (all types except Analog Input Flowmeter) Address Map.....	22
5.3.3.2	Analog Input Flowmeter Address Map	23
5.3.4	Digital Input Address Maps.....	24
5.3.4.1	Digital Input / DI State Type Address Map.....	24
5.3.4.2	Digital Input / Contacting Flow Meter Type Address Map.....	25
5.3.4.3	Digital Input / Paddlewheel Flow Meter Type Address Map.....	26
5.3.4.4	Digital Input / DI Counter Type Address Map	27
5.3.4.5	Digital Input / Flow Monitor Type Address Map.....	28
5.3.4.6	Digital Input / Remote Modbus Type Address Map	29
5.3.5	Virtual Input Address Maps.....	30
5.3.5.1	Virtual Input / Calculation Type Address Map	30
5.3.5.2	Virtual Input / Raw Value Type Address Map	31
5.3.5.3	Virtual Input / Redundant Sensor Type Address Map	32
5.3.5.4	Virtual Input / Disturbance Type Address Map.....	33
5.3.5.5	Virtual Input / Remote Modbus Type Address Map.....	34
5.3.6	Relay Output Address Maps.....	35
5.3.6.1	Relay Output / Manual Control Mode Address Map.....	35
5.3.6.2	Relay Output / On/Off Control Mode Address Map.....	36
5.3.6.3	Relay Output / On/Off Disturbance Control Mode Address Map.....	37
5.3.6.4	Relay Output / Dual Setpoint Control Mode Address Map	38
5.3.6.5	Relay Output / Time Proportional Control Mode Address Map	39
5.3.6.6	Relay Output / Intermittent Sampling Control Mode Address Map.....	40
5.3.6.7	Relay Output / Bleed And Feed Control Mode Address Map	41
5.3.6.8	Relay Output / Bleed Then Feed Control Mode Address Map.....	42
5.3.6.9	Relay Output / Flow Timer Control Mode Address Map	43
5.3.6.10	Relay Output / Counter Timer Control Mode Address Map	44
5.3.6.11	Relay Output / Target PPM Control Mode Address Map.....	45
5.3.6.12	Relay Output / PPM By Volume Control Mode Address Map.....	46
5.3.6.13	Relay Output / Flow Meter Ratio Control Mode Address Map	47
5.3.6.14	Relay Output / Volumetric Blend Control Mode Address Map.....	48
5.3.6.15	Relay Output / Dual Switch Control Mode Address Map	49
5.3.6.16	Relay Output / Boolean Logic Control Mode Address Map.....	50
5.3.6.17	Relay Output / Percent Timer Control Mode Address Map.....	51
5.3.6.18	Relay Output / Event Timer Control Mode Address Map.....	52
5.3.6.19	Relay Output / Biocide Timer Control Mode Address Map	53
5.3.6.20	Relay Output / Spike Control Mode Address Map.....	54
5.3.6.21	Relay Output / Probe Wash Control Mode Address Map.....	55
5.3.6.22	Relay Output / Plating Control Mode Address Map.....	56
5.3.6.23	Relay Output / Plating Follow Control Mode Address Map	57
5.3.6.24	Relay Output / Lag Output Control Mode Address Map.....	58
5.3.6.25	Relay Output / Alarm Control Mode Address Map	59

5.3.7	<i>Pulse Relay Output Address Maps</i>	60
5.3.7.1	<i>Pulse Relay Output / Manual Control Mode Address Map</i>	60
5.3.7.2	<i>Pulse Relay Output / Pulse Proportional Control Mode Address Map</i>	61
5.3.7.3	<i>Pulse Relay Output / Flow Proportional Control Mode Address Map</i>	62
5.3.7.4	<i>Pulse Relay Output / Pulse PID Control Mode Address Map</i>	63
5.3.7.5	<i>Pulse Relay Output / Pulse Disturbance Control Mode Address Map</i>	64
5.3.7.6	<i>Pulse Relay Output / Lag Output Control Mode Address Map</i>	65
5.3.8	<i>Analog Output Address Maps</i>	66
5.3.8.1	<i>Analog Output / Manual Control Mode Address Map</i>	66
5.3.8.2	<i>Analog Output / Retransmit Mode Address Map</i>	67
5.3.8.3	<i>Analog Output / Proportional Control Mode Address Map</i>	68
5.3.8.4	<i>Analog Output / Flow Proportional Control Mode Address Map</i>	69
5.3.8.5	<i>Analog Output / PID Control Mode Address Map</i>	70
5.3.8.6	<i>Analog Output / Disturbance Control Mode Address Map</i>	71
5.3.8.7	<i>Analog Output / Lag Output Control Mode Address Map</i>	72
5.3.9	<i>Alternate Address Maps</i>	73
5.3.9.1	<i>Alternate Sensor Input Address Map</i>	73
5.3.9.2	<i>Alternate Digital Input Address Map</i>	75
5.3.9.3	<i>Alternate Virtual Input Address Map</i>	76
5.3.9.4	<i>Alternate Relay Output Address Map</i>	77
5.3.9.5	<i>Alternate Analog Output Address Map</i>	78
5.3.9.6	<i>Alternate Control Output Address Map</i>	79
5.4	STATUS REGISTER CODES	80
5.5	ALARM BITFIELDS.....	83
5.5.1	<i>System Alarm Bitfield</i>	83
5.5.2	<i>Network Alarm Bitfield</i>	83
5.5.3	<i>Sensor Input Alarm Bitfield</i>	84
5.5.4	<i>Digital Input Alarm Bitfield</i>	84
5.5.5	<i>Virtual Input Alarm Bitfield</i>	85
5.5.6	<i>Relay & Control Output Alarm Bitfield</i>	85
5.5.7	<i>Analog Output Alarm Bitfield</i>	86

1.0 SCOPE

This document is a User Interface Specification for the Pulse Modbus/TCP product feature for EP200, EP1000, EP200N, and EP2100 Controllers. It contains mapping of the various dynamic variables to their Modbus/TCP address locations.

This document supports the Modbus/TCP feature on controller software versions 3.01 and higher.

2.0 INTRODUCTION

The Modbus/TCP feature allows the Pulse controller to communicate with PC-based applications such as WonderWare and Intellution HMI/SCADA programs, Building Energy Management systems, Distributed Control Systems (DCS), as well as stand-alone HMI devices.

The controller is a Modbus Server, meaning that it can respond to requests from the HMI device. The controller cannot initiate the flow of information. For example, it will not immediately send a new alarm message. It will wait until the HMI device requests the current data contained in specific address locations.

If the HMI device does not directly support the Modbus/TCP protocol, then a protocol translation gateway may be required to convert from Modbus/TCP to a protocol that the device supports. Please note that Modbus/RTU requires a serial interface, not Ethernet, and therefore is not directly compatible with the Pulse controller.

3.0 OVERVIEW

Modbus/TCP, also known as Modbus TCP/IP, is a form of Modbus that uses the TCP/IP layers as a base for controlling the communications between different devices. This is not to be confused with Modbus over TCP/IP, which Pulse controllers do not support.

The Modbus/TCP protocol supports multiple types of data transactions, from reading single bits per transaction, to advanced object-oriented operations. However, to ensure the most compatible system available, only a basic subset of these functions is supported in the controller.

The official Modbus/TCP protocol supports data addresses 5 digits in length. A *de facto* extended standard exists which supports data addresses 6 digits in length. However, to ensure compatibility, the Modbus/TCP feature supports only 5-digit data address system.

The Modbus/TCP feature supports reading and writing of single-bit Coils and 16-bit Holding Registers, as well as read-only single-bit Discrete Inputs and 16-bit Input Registers. These data formats allow the controller to establish blocks that contain all the process variables, set points, alarms, and input/output status values that are made public to a Modbus/TCP client. These blocks of data are packaged so that it can be read in 8-bit chunks (for a group of up to 8 Coils or Discrete Inputs) or 16-bit chunks (for a single Holding Register or Input Register), regardless of the type of data within it. In the following sections, the formatting, storing, and reading of this data are described.

3.1 Modbus Settings

Settings relating to the Modbus/TCP feature can be configured in the Remote Communication Configuration Menu.

The 'Verbose Logging' setting is used to generate an Event log entry for every Modbus message into and out of the controller. The information may be used in conjunction with an HMI log when troubleshooting communications during commissioning. However, the additional logging adds a significant load on the controller's systems. Therefore, this feature should only be enabled temporarily while actively troubleshooting communications. The setting automatically reverts to Disabled when the controller is restarted.

Detailed information on the Remote Communication Configuration Menu can be found in the controller Instruction Manual.

4.0 MODBUS/TCP DRIVER

4.1 Modbus/TCP Protocol

The Modbus protocol, as well as the Modbus/TCP variant, is well documented in the specifications which are available at <http://www.modbus.org>, a website established by the Modbus Organization for supporting and organizing the Modbus protocol.

The Modbus/TCP Application Data Unit (ADU) consists of 2 distinct sections:

Modbus Application Protocol (MBAP)
Header

Protocol Data Unit (PDU)

The total size of the ADU is between 9 and 263 bytes, depending on the function code and number of data addresses requested.

4.1.1 MBAP Header

The Modbus/TCP extension adds 7 additional bytes to the original Modbus protocol, which allows for the transport over the TCP/IP layers. These 7 bytes make up the MBAP Header:

Modbus Application Protocol (MBAP) Header		
Name	Size	Description
Transaction Identifier	2 bytes	Identification of Request/Response transaction. Copied from request to response
Protocol Identifier	2 bytes	0 = Modbus protocol.
Length	2 bytes	Number of following bytes (includes the Unit Identifier and PDU)
Unit Identifier	1 byte	Identification of Remote Device. Can be used for broadcasting (unsupported).

The Unit Identifier has a special consideration in the Modbus/TCP implementation. If the value is 0, then the request is a broadcast message and the packet will be processed, but no response will be generated. If the value is non-zero, the packet will be processed and a response will be returned.

Normally the Slave ID, which is not present in the Modbus/TCP protocol, will be set in the HMI client software to 1. The broadcast Unit Identifier address is not supported by the controller; all supported function codes require a response message at all times.

4.1.2 Protocol Data Unit

The Protocol Data Unit (PDU) is made up of between 2 and 256 bytes, depending on the function and number of data addresses requested:

Protocol Data Unit (PDU)		
Name	Size	Description
Function Code	1 byte	Function Code identifier. Can be any of the hexadecimal codes listed in the Function Code table.
Data Payload	1 – 255 byte(s)	Payload for request/response transactions. Varies depending on function code and number of addresses requested.

4.1.3 Modbus/TCP Function Codes

The Modbus/TCP Server feature supports the following function codes:

Supported Function Codes			
Function Code	Name	Description	Data Address Range
FC1 (0x01)	Read Coils	Read up to 2000 consecutive 1-bit Coils within a single request/response cycle.	0xxxx
FC2 (0x02)	Read Discrete Inputs	Read up to 2000 consecutive 1-bit Discrete Inputs within a single request/response cycle.	1xxxx
FC3 (0x03)	Read Holding Registers	Read up to 125 consecutive 16-bit Holding Registers within a single request/response cycle.	4xxxx
FC4 (0x04)	Read Input Registers	Read up to 125 consecutive 16-bit Input Registers within a single request/response cycle.	3xxxx
FC5 (0x05)	Write Single Coil	Write a single 1-bit Coil within a single request/response cycle.	0xxxx
FC6 (0x06)	Write Single Holding Register	Write a single 16-bit Holding Register within a single request/response cycle.	4xxxx
FC16 (0x10)	Write Multiple Holding Registers	Write up to 125 consecutive 16-bit Holding Registers within a single request/response cycle.	4xxxx

The consecutive address limitations of the Coils, Discrete Inputs, Holding Registers, and Input Registers were established for the Modbus/TCP standard to maintain consistency with the original Modbus protocol standard, even though a TCP/IP packet can contain a larger payload.

The Modbus/TCP feature allows for Function Codes 1 and 2 to be used interchangeably for read requests. For example, a read coils (FC1) request for data addresses 00605 through 00610 will always return the same result as a read discrete inputs (FC2) request for data addresses 10605 through 10610.

Likewise, the Modbus/TCP feature allows for Function Codes 3 and 4 to also be used interchangeably for read requests. For example, a read holding registers (FC3) request for data addresses 40587 through 40590 will always return the same result as a read input registers (FC4) request for data addresses 30587 through 30590. All addresses accessible as a Coil or Discrete Input may also be accessed as a Holding Register or Input Register.

Only the 4 least significant digits of the data address are explicitly stated in the Modbus message, with the most significant (5th) digit being derived from the function code. However, generally the entire 5-digit data address must be specified in the Tag Database of an HMI.

4.1.3.1 Function Code 1, Read Coils

Read Coils Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x01).
Starting Address	2 Bytes	The data address of the first Coil to read.
Quantity of Coils	2 Bytes	The number of Coils requested, maximum of 2000 per message.

Read Coils Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x01).
Byte Count	1 Byte	The number of data bytes to follow.
Coil Status	1-125 Bytes	8 Coils per byte, up to 2000 Coils per message.

Read Coils Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x81).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.3.2 Function Code 2, Read Discrete Inputs

Read Discrete Inputs Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x02).
Starting Address	2 Bytes	The data address of the first Discrete Input to read.
Quantity of Discrete Inputs	2 Bytes	The number of Discrete Inputs requested, maximum of 2000 per message.

Read Discrete Inputs Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x02).
Byte Count	1 Byte	The number of data bytes to follow.
Discrete Input Status	1-125 Bytes	8 Discrete Inputs per byte, up to 2000 Discrete Inputs per message.

Read Discrete Inputs Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x82).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.3.3 Function Code 3, Read Holding Registers

Read Holding Registers Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x03).
Starting Address	2 Bytes	The data address of the first Holding Register to read.
Quantity of Holding Registers	2 Bytes	The total number of Holding Registers requested, maximum of 125 per message.

Read Holding Registers Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x03).
Byte Count	1 Byte	The number of data bytes to follow.
Holding Register Values	2-250 Bytes	1 Holding Register for every 2 bytes, maximum of 125 Holding Registers per message.

Read Holding Registers Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x83).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.3.4 Function Code 4, Read Input Registers

Read Input Registers Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x04).
Starting Address	2 Bytes	The data address of the first Input Register to read.
Quantity of Input Registers	2 Bytes	The total number of Input Registers requested, maximum of 125 per message.

Read Input Registers Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x04).
Byte Count	1 Byte	The number of data bytes to follow.
Input Register Values	2-250 Bytes	1 Input Register for every 2 bytes, maximum of 125 Input Registers per message.

Read Input Registers Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x84).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.3.5 Function Code 5, Write Single Coil

Write Single Coil Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x05).
Coil Address	2 Bytes	The data address of the Coil to which to write.
Coil Value	2 Bytes	The value to write to the Coil (0xFF00 = On, 0x0000 = Off).

Write Single Coil Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x05).
Coil Address	2 Bytes	The data address of the Coil written.
Coil Value	2 Bytes	The value written to the Coil (0xFF00 = On, 0x0000 = Off).

Write Single Coil Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x85).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.3.6 Function Code 6, Write Single Holding Register

Write Single Holding Register Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x06).
Holding Register Address	2 Bytes	The data address of the Holding Register to which to write.
Holding Register Value	2 Bytes	The value to write to the Holding Register.

Write Single Holding Register Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x06).
Holding Register Address	2 Bytes	The data address of the Holding Register written.
Holding Register Value	2 Bytes	The value written to the Holding Register.

Write Single Holding Register Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x86).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.3.7 Function Code 16, Write Multiple Holding Registers

Write Multiple Holding Registers Request PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x10).
Starting Address	2 Bytes	The data address of the first Holding Register to which to write.
Quantity of Holding Registers	2 Bytes	Number of Holding Registers to write.
Byte Count	1 Byte	The number of data bytes to follow.
Holding Register Values	1-250 Bytes	2 bytes for every Holding Register, maximum of 125 Holding Registers per message.

Write Multiple Holding Registers Response PDU		
Name	Size	Description
Function Code	1 Byte	Function Code Identifier (0x10).
Starting Address	2 Bytes	The data address of the Holding Register written.
Quantity of Holding Registers	2 Bytes	Number of Holding Registers written.

Write Multiple Holding Registers Exception PDU		
Name	Size	Description
Error Code	1 Byte	0x80 plus Function Code Identifier (0x90).
Exception Code	1 Byte	See 4.1.4 Modbus/TCP Exception Error Codes

4.1.4 Modbus/TCP Exception Error Codes

The Modbus/TCP feature supports the following Exception (Error) Codes:

Supported Exception Codes		
Exception Code	Name	Description
0x01	Illegal Function	The function code received is not supported in the controller.
0x02	Illegal Data Address	The data address received is not an allowable address within the controller. This error will only be generated if the first register requested is not valid for the function.
0x03	Illegal Data Value	A value contained in the query data field for a <i>Write</i> command is not an allowable value for field. This error will only be generated if the first register requested is not valid for the function.
0x04	Slave Device Failure	An unrecoverable error occurred while the controller was attempting to perform the requested action. This is a general exception code indicating that the request was valid, but the controller could provide a response.

When an exception occurs, the Response PDU contains a Function Code of 0x80 plus the original hexadecimal Function Code.

4.2 TCP/IP Interface

The Modbus/TCP interface is attached to the TCP/IP stack that is implemented within the Pulse controller. When the Modbus feature is *Enabled*, the controller will listen to all communications that come in on the Modbus/TCP registered port 502. This port can be changed in the Remote Communications Menu.

4.3 Data Refresh

To ensure continued connectivity, the Modbus/TCP client should not request data more frequently than once every 5000 msec. Faster refresh rates are unsupported and may result in unexpected behavior.

4.4 Data Encoding

Modbus uses a 'big-endian' representation for addresses and data items. This means that within each register, when a numerical quantity larger than a single byte is transmitted, the MOST significant byte is sent first. The following topics describe the different types of encoding and show how the data is encoded within the Modbus/TCP packet. Most client drivers will extract the data from the packet in the correct format for use/display within the client environment.

4.4.1 Coils and Discrete Inputs

4.4.1.1 Boolean

Coils and Discrete Inputs can be used for digital input states, relay states, alarm states, and reset buttons that are representable as a 1 or a 0. All binary data is packed from least significant bit to most significant bit into a byte containing up to 8 Coils or Discrete Inputs. Bits not containing the value of a Coil or Discrete Input are space holders and have a value of 0.

Byte Value	Coil 1	Coil 2	6 unused bits
0x02 (00000010)	0	1	000000

Reset buttons may also be packed as a 16-bit word when using the Write Single Coil function code. (0xFF00 = On, 0x0000 = Off)

Word Value	Coil Value	Most Significant Byte	Least Significant Byte
0xFF00 (1111111100000000)	1	0xFF (11111111)	0x00 (00000000)

4.4.2 Holding Register and Input Registers

4.4.2.1 16-Bit Word (Boolean)

Holding Registers and Input Registers can be used for digital input states, relay states, alarm states, and reset buttons that are representable as a 1 or a 0. All binary data can be packed into a 16-Bit register, with the least significant bit of the least significant byte being occupied by the 1-bit value. This is functionally identical to a 16-bit integer.

Word Value	Bit Value	Most Significant Byte	Least Significant Byte
0x0001 (0000000000000001)	1	0x00 (00000000)	0x01 (00000001)

4.4.2.2 16-Bit Word (Bitfield)

Holding Registers and Input Registers can be used for Alarm Bitfields. An 8-Bit Alarm bitfield is packed into the least significant byte of a 16-bit register. This is offered as a single-register alternative to accessing alarm states individually. Bitfields can be decoded in section [5.5 Alarm Bitfields](#).

Word Value	Alarm Bitfield Value	Most Significant Byte	Least Significant Byte
0x00AA (0000000010101010)	0xAA	0x00 (00000000)	0xAA (10101010)

4.4.2.3 16-Bit Word (Status)

Holding Registers and Input Registers can be used for enumerated values such as status codes. An 8-Bit status code is packed into the least significant byte of a 16-bit register. This is functionally identical to the 16-bit integer. Status codes are defined in section [5.4 Status Register Codes](#).

Word Value	Alarm Bitfield Value	Most Significant Byte	Least Significant Byte
0x00AA (0000000010101010)	0xAA	0x00 (00000000)	0xAA (10101010)

4.4.2.4 16-Bit Word (Integer)

Holding Registers and Input Registers can be used for 16-bit integers containing HOA settings, and time data that don't require 32-bit integers. All 16-bit integers are unsigned.

Word Value	Most Significant Byte	Least Significant Byte
0x1234	0x12	0x34

4.4.2.5 32-Bit Value (Integer)

Holding Registers and Input Registers can be used for 32-bit integer data containing elapsed time values and timestamps. The system clock register and all registers containing timestamps use the Unix Time format, that counts the seconds passed since 12:00:00 am, January 1st, 1970. Registers are only 16 bits wide; therefore, a request message must include 2 consecutive registers to read or write a 32-bit integer. The 32-bit value is transmitted with the least significant word first, then the most significant word. All 32-bit integers are unsigned.

Word Value	Register 1		Register 2	
	Most Significant	Least Significant	Most Significant	Least Significant
	Least Significant Word		Most Significant Word	
0x12345678	0x56	0x78	0x12	0x34

4.4.2.6 32-Bit Value (Float)

Holding Registers and Input Registers can be used for 32-bit floating point data containing set points, sensor readings, percentages, deadbands, etc. Registers are only 16 bits wide; therefore, a request message must include 2 consecutive registers to read or write a 32-bit float. The 32-bit value is transmitted with the least significant word first, then the most significant word.

Word Value	Register 1		Register 2	
	Most Significant	Least Significant	Most Significant	Least Significant
	Least Significant Word		Most Significant Word	
0x12345678	0x56	0x78	0x12	0x34

4.4.2.7 32-Bit Inverse Data Format (Integer or Float)

32-bit integers and floats can use an inverse data format, where the contents of registers 1 and 2 are switched. When inverse data format is selected, the 32-bit value is transmitted with the most significant word first, then the least significant word. The data format setting can be modified in the Remote Communications Settings Menu.

Word Value	Register 1		Register 2	
	Most Significant	Least Significant	Most Significant	Least Significant
	Most Significant Word		Least Significant Word	
0x12345678	0x12	0x34	0x56	0x78

5.0 DATA DICTIONARY

5.1 Addressing (0- or 1-Based)

The addressing within the Modbus/TCP protocol (that is, the data within the physical packet) is 0-based, meaning the first element/item to be accessed is referenced by address 0. The Modbus standard for handling and displaying data is 1-based, meaning the first element/data item to be accessed is referenced by address 1.

For most client applications, users enter the 1-based number which is converted to 0-based addressing at the protocol level. The addresses defined in the following address maps below are 1-based, as most of the client applications work with this method. Register addresses for individual elements are derived by adding the address offset in the appropriate [Type-Specific Address Map](#) to the starting address in the I/O Channel Address Map below.

5.2 Address Maps

The address map is a function code-agnostic map that contains all data values that can be accessed as Coils (0xxxx), Discrete Inputs (1xxxx), Holding Registers (4xxxx), and Input Registers (3xxxx).

The Address Map of the Modbus/TCP feature is modular; valid addresses are determined by the add-on card configuration of the controller and the task being performed by each Input or Output. Each object has a block of 36 addresses.

The Modbus/TCP feature allows all addresses to be accessed as registers. On the following address map tables, values in **BOLD** can also be accessed as a Coil or Discrete Input.

As examples, to read the 'Controller Firmware Version' from the [System Address Map](#) (starting address x0037) as an Input Register (FC4), the address indices 2 and 3 must be requested together: Addresses 30039 and 30040.

To read the 'Low Alarm' status for Sensor 2-1 in a EP200 Controller as a Coil (FC1), the [Sensor Input Address Map](#) indicates the starting address is x0865. Address index 28 must be requested: Address 00893. For the EP1000 Controller, the 'Low Alarm' status for Sensor 2-1 is $x1729 + 28 = \text{Address } 01757$.

To write the 'Setpoint' for Relay 3 (set to On/Off control mode) in the [Relay On/Off Control Mode Address Map](#) (starting address x9001) as a Holding Register (FC6), the address indices 6 and 7 must be used together: Addresses 49007 and 49008.

5.2.1 EP200 Controller – I/O Channel Address Maps

The address ranges for each input/output channel in the EP200 controller are as follows:

EP200 Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
System	x0037	x0072	See 5.3.1 System Address Map
Network	x0145	x0180	See 5.3.2 Network Address Map
Sensor Input 1-1	x0577	x0612	See 5.3.3 Sensor Input Address Maps
Sensor Input 1-2	x0613	x0648	
Sensor Input 1-3	x0649	x0684	
Sensor Input 2-1	x0865	x0900	
Sensor Input 2-2	x0901	x0936	
Sensor Input 2-3	x0937	x0972	
Digital Input 1	x0289	x0324	See 5.3.4 Digital Input Address Maps
Digital Input 2	x0325	x0360	
Digital Input 3	x0361	x0396	
Digital Input 4	x0397	x0432	
Digital Input 5	x0433	x0468	
Digital Input 6	x0469	x0504	
Virtual Input 1	x5761	x5796	See 5.3.5 Virtual Input Address Maps
Virtual Input 2	x5797	x5832	
Relay Output 1	x8929	x8964	See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps
Relay Output 2	x8965	x9000	
Relay Output 3	x9001	x9036	
Relay Output 4	x9037	x9072	
Relay Output 5	x9073	x9108	
Relay Output 6	x9109	x9144	
Analog Output 1	x1153	x1188	See 5.3.8 Analog Output Address Maps
Analog Output 2	x1189	x1224	

5.2.2 EP1000 Controller – I/O Channel Address Maps

The address ranges for each input/output channel in the Ep1000 controller are as follows:

EP1000 Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
System	x0037	x0072	See 5.3.1 System Address Map
Network	x0145	x0180	See 5.3.2 Network Address Map
Sensor Input 1-1	x1153	x1188	See 5.3.3 Sensor Input Address Maps Note: When using P/N 191918 I/O card with 2 Analog Input + 4 Analog Output channels, the two (4-20 mA) Sensor Inputs are mapped from channels 1 and 2 into channels 5 and 6. For example, if the card is installed in the third I/O slot, the register address mapping is: Analog Output 3-1: x2305 to x2340 Analog Output 3-2: x2341 to x2376 Analog Output 3-3: x2377 to x2412 Analog Output 3-4: x2413 to x2448 Sensor Input 3-1: x2449 to x2484 Sensor Input 3-2: x2485 to x2520
Sensor Input 1-2	x1189	x1224	
Sensor Input 1-3	x1225	x1260	
Sensor Input 1-4	x1261	x1296	
Sensor Input 1-5	x1297	x1332	
Sensor Input 1-6	x1333	x1368	
Sensor Input 2-1	x1729	x1764	
Sensor Input 2-2	x1765	x1800	
Sensor Input 2-3	x1801	x1836	
Sensor Input 2-4	x1837	x1872	
Sensor Input 2-5	x1873	x1908	
Sensor Input 2-6	x1909	x1944	
Sensor Input 3-1	x2305	x2340	
Sensor Input 3-2	x2341	x2376	
Sensor Input 3-3	x2377	x2412	
Sensor Input 3-4	x2413	x2448	
Sensor Input 3-5	x2449	x2484	
Sensor Input 3-6	x2485	x2520	
Sensor Input 4-1	x2881	x2916	
Sensor Input 4-2	x2917	x2952	
Sensor Input 4-3	x2953	x2988	
Sensor Input 4-4	x2989	x3024	
Sensor Input 4-5	x3025	x3060	
Sensor Input 4-6	x3061	x3096	
Digital Input 1	x0577	x0612	See 5.3.4 Digital Input Address Maps
Digital Input 2	x0613	x0648	
Digital Input 3	x0649	x0684	
Digital Input 4	x0685	x0720	
Digital Input 5	x0721	x0756	
Digital Input 6	x0757	x0792	
Digital Input 7	x0793	x0828	
Digital Input 8	x0829	x0864	
Digital Input 9	x0865	x0900	
Digital Input 10	x0901	x0936	
Digital Input 11	x0937	x0972	
Digital Input 12	x0973	x1008	

EP1000 Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
Virtual Input 1	x5761	x5796	See 5.3.5 Virtual Input Address Maps
Virtual Input 2	x5797	x5832	
Virtual Input 3	x5833	x5868	
Virtual Input 4	x5869	x5904	
Virtual Input 5	x5905	x5940	
Virtual Input 6	x5941	x5976	
Virtual Input 7	x5977	x6012	
Virtual Input 8	x6013	x6048	
Relay Output 1	x8929	x8964	See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps
Relay Output 2	x8965	x9000	
Relay Output 3	x9001	x9036	
Relay Output 4	x9037	x9072	
Relay Output 5	x9073	x9108	
Relay Output 6	x9109	x9144	
Relay Output 7	x9145	x9180	
Relay Output 8	x9181	x9144	
Analog Output 1-1	x1153	x1188	See 5.3.8 Analog Output Address Maps
Analog Output 1-2	x1189	x1224	
Analog Output 1-3	x1225	x1260	
Analog Output 1-4	x1261	x1296	
Analog Output 2-1	x1729	x1764	
Analog Output 2-2	x1765	x1800	
Analog Output 2-3	x1801	x1836	
Analog Output 2-4	x1837	x1872	
Analog Output 3-1	x2305	x2340	
Analog Output 3-2	x2341	x2376	
Analog Output 3-3	x2377	x2412	
Analog Output 3-4	x2413	x2448	
Analog Output 4-1	x2881	x2916	
Analog Output 4-2	x2917	x2952	
Analog Output 4-3	x2953	x2988	
Analog Output 4-4	x2989	x3024	
Control Output 1	x6913	x6948	See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps Note: Control Outputs share address maps and alarm bitfields with Relay control modes
Control Output 2	x6949	x6984	
Control Output 3	x6985	x7020	
Control Output 4	x7021	x7056	
Control Output 5	x7057	x7092	
Control Output 6	x7093	x7128	
Control Output 7	x7129	x7164	
Control Output 8	x7165	x7200	

5.2.3 EP200N Controller – I/O Channel Address Maps

The address ranges for each input/output channel in the EP200N controller are as follows:

EP200N Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
System	x0037	x0072	See 5.3.1 System Address Map
Network	x0145	x0180	See 5.3.2 Network Address Map
Sensor Input 1-1	x0577	x0612	See 5.3.3 Sensor Input Address Maps
Sensor Input 1-2	x0613	x0648	
Sensor Input 1-3	x0649	x0684	
Sensor Input 2-1	x0865	x0900	
Sensor Input 2-2	x0901	x0936	
Sensor Input 2-3	x0937	x0972	
Digital Input 1	x0289	x0324	See 5.3.4 Digital Input Address Maps
Digital Input 2	x0325	x0360	
Digital Input 3	x0361	x0396	
Digital Input 4	x0397	x0432	
Digital Input 5	x0433	x0468	
Digital Input 6	x0469	x0504	
Virtual Input 1	x5761	x5796	See 5.3.5 Virtual Input Address Maps
Virtual Input 2	x5797	x5832	
Virtual Input 3	x5833	x5868	
Virtual Input 4	x5869	x5904	
Virtual Input 5	x5905	x5940	
Virtual Input 6	x5941	x5976	
Relay Output 1	x8929	x8964	See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps
Relay Output 2	x8965	x9000	
Relay Output 3	x9001	x9036	
Relay Output 4	x9037	x9072	
Relay Output 5	x9073	x9108	
Relay Output 6	x9109	x9144	
Analog Output 1	x1153	x1188	See 5.3.8 Analog Output Address Maps
Analog Output 2	x1189	x1224	
Control Output 1	x6913	x6948	See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps Note: Control Outputs share address maps and alarm bitfields with Relay control modes
Control Output 2	x6949	x6984	
Control Output 3	x6985	x7020	
Control Output 4	x7021	x7056	
Control Output 5	x7057	x7092	
Control Output 6	x7093	x7128	

5.2.4 EP2100 Controller – I/O Channel Address Maps

The address ranges for each input/output channel in the EP2100 controller are as follows:

EP2100 Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
System	x0037	x0072	See 5.3.1 System Address Map
Network	x0145	x0180	See 5.3.2 Network Address Map
Sensor Input 1-1	x1153	x1188	See 5.3.3 Sensor Input Address Maps Note: When using P/N 191918 I/O card with 2 Analog Input + 4 Analog Output channels, the two (4-20 mA) Sensor Inputs are mapped from channels 1 and 2 into channels 5 and 6. For example, if the card is installed in the third I/O slot, the register address mapping is: Analog Output 3-1: x2305 to x2340 Analog Output 3-2: x2341 to x2376 Analog Output 3-3: x2377 to x2412 Analog Output 3-4: x2413 to x2448 Sensor Input 3-1: x2449 to x2484 Sensor Input 3-2: x2485 to x2520
Sensor Input 1-2	x1189	x1224	
Sensor Input 1-3	x1225	x1260	
Sensor Input 1-4	x1261	x1296	
Sensor Input 1-5	x1297	x1332	
Sensor Input 1-6	x1333	x1368	
Sensor Input 2-1	x1729	x1764	
Sensor Input 2-2	x1765	x1800	
Sensor Input 2-3	x1801	x1836	
Sensor Input 2-4	x1837	x1872	
Sensor Input 2-5	x1873	x1908	
Sensor Input 2-6	x1909	x1944	
Sensor Input 3-1	x2305	x2340	
Sensor Input 3-2	x2341	x2376	
Sensor Input 3-3	x2377	x2412	
Sensor Input 3-4	x2413	x2448	
Sensor Input 3-5	x2449	x2484	
Sensor Input 3-6	x2485	x2520	
Sensor Input 4-1	x2881	x2916	
Sensor Input 4-2	x2917	x2952	
Sensor Input 4-3	x2953	x2988	
Sensor Input 4-4	x2989	x3024	
Sensor Input 4-5	x3025	x3060	
Sensor Input 4-6	x3061	x3096	
Digital Input 1	x0289	x0324	See 5.3.4 Digital Input Address Maps
Digital Input 2	x0325	x0360	
Digital Input 3	x0361	x0396	
Digital Input 4	x0397	x0432	
Digital Input 5	x0433	x0468	
Digital Input 6	x0469	x0504	
Digital Input 7	x0505	x0540	
Digital Input 8	x0541	x0576	
Digital Input 9	x0577	x0612	
Digital Input 10	x0613	x0648	
Digital Input 11	x0649	x0684	
Digital Input 12	x0685	x0720	

EP2100 Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
Virtual Input 1	x5761	x5796	See 5.3.5 Virtual Input Address Maps
Virtual Input 2	x5797	x5832	
Virtual Input 3	x5833	x5868	
Virtual Input 4	x5869	x5904	
Virtual Input 5	x5905	x5940	
Virtual Input 6	x5941	x5976	
Virtual Input 7	x5977	x6012	
Virtual Input 8	x6013	x6048	
Virtual Input 9	x6049	x6084	
Virtual Input 10	x6085	x6120	
Virtual Input 11	x6121	x6156	
Virtual Input 12	x6157	x6192	
Virtual Input 13	x6193	x6228	
Virtual Input 14	x6229	x6264	
Virtual Input 15	x6265	x6300	
Virtual Input 16	x6301	x6336	
Relay Output 1	x8929	x8964	Fixed Relays See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps
Relay Output 2	x8965	x9000	
Relay Output 3	x9001	x9036	
Relay Output 4	x9037	x9072	
Relay Output 5	x9073	x9108	
Relay Output 6	x9109	x9144	
Relay Output 7	x9145	x9180	
Relay Output 8	x9181	x9144	
Relay Output 1-1	x8929	x8964	Field-Configurable Relays See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps
Relay Output 1-2	x8965	x9000	
Relay Output 1-3	x9001	x9036	
Relay Output 1-4	x9037	x9072	
Relay Output 2-1	x9073	x9108	
Relay Output 2-2	x9109	x9144	
Relay Output 2-3	x9145	x9180	
Relay Output 2-4	x9181	x9144	
Relay Output 3-1	x8641	x8676	
Relay Output 3-2	x8677	x8712	
Relay Output 3-3	x8713	x8748	
Relay Output 3-4	x8749	x8784	

EP2100 Controller – I/O Channel Address Map			
Object	Starting Address	Ending Address	Type-Specific Address Maps
Analog Output 1-1	x1153	x1188	See 5.3.8 Analog Output Address Maps
Analog Output 1-2	x1189	x1224	
Analog Output 1-3	x1225	x1260	
Analog Output 1-4	x1261	x1296	
Analog Output 2-1	x1729	x1764	
Analog Output 2-2	x1765	x1800	
Analog Output 2-3	x1801	x1836	
Analog Output 2-4	x1837	x1872	
Analog Output 3-1	x2305	x2340	
Analog Output 3-2	x2341	x2376	
Analog Output 3-3	x2377	x2412	
Analog Output 3-4	x2413	x2448	
Analog Output 4-1	x2881	x2916	
Analog Output 4-2	x2917	x2952	
Analog Output 4-3	x2953	x2988	
Analog Output 4-4	x2989	x3024	
Control Output 1	x6913	x6948	See 5.3.6 Relay Output Address Maps Or 5.3.7 Pulse Relay Output Address Maps Note: Control Outputs share address maps and alarm bitfields with Relay control modes
Control Output 2	x6949	x6984	
Control Output 3	x6985	x7020	
Control Output 4	x7021	x7056	
Control Output 5	x7057	x7092	
Control Output 6	x7093	x7128	
Control Output 7	x7129	x7164	
Control Output 8	x7165	x7200	
Control Output 9	x7201	x7236	
Control Output 10	x7237	x7272	
Control Output 11	x7273	x7308	
Control Output 12	x7309	x7344	
Control Output 13	x7345	x7380	
Control Output 14	x7381	x7416	
Control Output 15	x7417	x7452	
Control Output 16	x7453	x7488	

5.2.5 Alternate Address Maps

The I/O Address Maps in the previous sections are based on the hardware position/slot within the controller. Alternate Address Maps use software-based, dynamic addressing to provide a more efficient way to access similar data from different objects. Using these address tables, the same field type is accessible using consecutive addresses. For example, the primary values for all sensors installed in the controller can be accessed in a single Modbus FC4 request/response cycle starting at address 39217.

I/O Type	Available Objects	Type-Specific Alternate Address Map
Sensor Inputs (32 Channels)	Primary Value; Status Alarm Bitfield Low, High Alarms LoLo, HiHi Alarms Calibration Required	See 5.3.9.1 Alternate Sensor Input / Temperature Input / Analog Input Address Map
Digital Inputs (16 Channels)	DI State; Interlock State Total Time Flowrate; Flow Total Alarm Bitfield Low, High Alarms	See 5.3.9.2 Alternate Digital Input Address Map
Virtual Inputs (16 Channels)	Primary Value; Status Alarm Bitfield	See 5.3.9.3 Alternate Virtual Input Address Map
Relay Outputs (16 Channels)	Relay State Pulse Output Percent Time On; Status Alarm Bitfield	See 5.3.9.4 Alternate Relay Output Address Map
Analog Outputs (16 Channels)	Output Percent Time On; Status Alarm Bitfield	See 5.3.9.5 Alternate Analog Output Address Map
Control Outputs (16 Channels)	Output State Output Percent Time On; Status Alarm Bitfield	See 5.3.9.6 Alternate Control Output Address Map

Note that changing I/O card locations can affect the address used to access individual objects. For example, if an EP2100 controller is configured with a Dual SI card in slot 1 and a Dual AI card in slot 3, the address mappings for the primary values are different if a Single SI card is inserted into slot 2:

Scenario #1: I/O Slot 2 Not Populated				Scenario #2: I/O Slot 2 Populated			
Channel	Address	Alternate	Address	Channel	Address	Alternate	Address
I/O Slot 1: Dual Sensor Input Card				I/O Slot 1: Dual Sensor Input Card			
Sensor Input 1-1	x1153	Sensor 1	x9217	Sensor Input 1-1	x1153	Sensor 1	x9217
Sensor Input 1-2	x1189	Sensor 2	x9219	Sensor Input 1-2	x1189	Sensor 2	x9219
Sensor Input 1-3	x1225	Sensor 3	x9221	Sensor Input 1-3	x1225	Sensor 3	x9221
Sensor Input 1-4	x1261	Sensor 4	x9223	Sensor Input 1-4	x1261	Sensor 4	x9223
I/O Slot 2: Not Populated				I/O Slot 2: Single Sensor Input Card			
				Sensor Input 2-1	x1729	Sensor 5	x9225
				Sensor Input 2-2	x1765	Sensor 6	x9227
I/O Slot 3: Dual Analog Input Card				I/O Slot 3: Dual Analog Input Card			
Sensor Input 3-1	x2305	Sensor 5	x9225	Sensor Input 3-1	x2305	Sensor 7	x9229
Sensor Input 3-2	x2341	Sensor 6	x9227	Sensor Input 3-2	x2341	Sensor 8	x9231

5.3 Type-Specific Address Maps

5.3.1 System Address Map

System Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Controller Time	32-Bit Integer	Read	Unix Time
1				
2	Controller Firmware Version	32-Bit Float	Read	
3				
4	Date of Last Data Log	32-Bit Integer	Read	Unix Time
5				
6	Controller Processor Temperature	32-Bit Float	Read	°C
7				
8	Network Card Temperature	32-Bit Float	Read	°C
9				
10	Digital Input Card Temp †	32-Bit Float	Read	°C
11				
12	I/O Card 1 Temperature	32-Bit Float	Read	°C
13				
14	I/O Card 2 Temperature	32-Bit Float	Read	°C
15				
16	I/O Card 3 Temperature †	32-Bit Float	Read	°C
17				
18	I/O Card 4 Temperature †	32-Bit Float	Read	°C
19				
20				
21				
22				
23				
24				
25				
26	Battery Power	32-Bit Float	Read	Volt
27				
28	+3.3 V Supply	32-Bit Float	Read	Volt
29				
30	+5 V Supply	32-Bit Float	Read	Volt
31				
32	+12 V Supply †	32-Bit Float	Read	Volt
33				
34				
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.1 System Alarm Bitfield

† Field is only available for EP1000 and EP2100 Controllers.

5.3.2 Network Address Map

Network Address Map							
Address	Name	Data Encoding	Permissions	Value			
0	Fluent Last Data Time	32-Bit Integer	Read	Unix Time			
1							
2	Fluent Last Configuration Time	32-Bit Integer	Read	Unix Time			
3							
4	Fluent Refresh Rate	32-Bit Float	Read/Write	1 – 1440 Minutes			
5							
6	Fluent LiveConnect Status	16-Bit Status	Read	See 5.4 Status Register Codes			
7	WebServer Status	16-Bit Status	Read	See 5.4 Status Register Codes			
8							
9							
10							
11							
12							
13							
14							
15							
16							
17							
18	WiFi Signal Strength †	32-Bit Float	Read	-30 – -100 dBm			
19							
20	WiFi RSSI †	32-Bit Float	Read	0 – 100%			
21							
22	WiFi Channel †	32-Bit Float	Read	1 – 14			
23							
24	WiFi Security †	16-Bit Status	Read	See 5.4 Status Register Codes			
25	WiFi Status †	16-Bit Status	Read	See 5.4 Status Register Codes			
26	Begin Temporary Ad-Hoc Mode Session †	Boolean	Read/Write	Write 1 to Begin Temporary Ad-Hoc Mode Session			
27	End Temporary Ad-Hoc Mode Session †	Boolean	Read/Write	Write 1 to End Temporary Ad-Hoc Mode Session			
28	Ad-Hoc Mode Time Limit †	32-Bit Float	Read/Write	1 – 1440 minutes			
29							
30							
31							
32							
33							
34							
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.2 Network Alarm Bitfield			

† Field is only available for EP1000 and EP2100 Controllers.

5.3.3 Sensor Input Address Maps

5.3.3.1 Sensor Input (all types except Analog Input Flowmeter) Address Map

Sensor Input (all types except Analog Input Flowmeter) Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Primary Value	32-Bit Float	Read	Sensor Units
1				
2	Primary Raw Value	32-Bit Float	Read	Conductivity: μS/cm before ATC Active, Cu/Ni: mV 4-20 mA Input: mA Temperature: Ω Corrosion Rate: Mild Steel mpy Imbalance: Corr/Imb
3				
4	Last Calibration Date	32-Bit Integer	Read	Unix Time
5				
6				
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Sensor Units
11				
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14	LoLo Alarm Setpoint	32-Bit Float	Read/Write	Sensor Units
15				
16	Low Alarm Setpoint	32-Bit Float	Read/Write	Sensor Units
17				
18	High Alarm Setpoint	32-Bit Float	Read/Write	Sensor Units
19				
20	HiHi Alarm Setpoint	32-Bit Float	Read/Write	Sensor Units
21				
22	24-Hour Minimum †	32-Bit Float	Read	Sensor Units
23				
24	24-Hour Maximum †	32-Bit Float	Read	Sensor Units
25				
26	24-Hour Average †	32-Bit Float	Read	Sensor Units
27				
28	Low Alarm	Boolean	Read	1 = Alarm Active
29	High Alarm	Boolean	Read	1 = Alarm Active
30	LoLo Alarm	Boolean	Read	1 = Alarm Active
31	HiHi Alarm	Boolean	Read	1 = Alarm Active
32	Cal Required	Boolean	Read	1 = Alarm Active
33	Input Failure	Boolean	Read	1 = Alarm Active
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.3 Sensor Input Alarm Bitfield

† Field is only available for EP1000 and EP2100 Controllers.

5.3.3.2 Analog Input Flowmeter Address Map

Analog Input Flowmeter Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Primary Flowrate	32-Bit Float	Read	<u>Flow Units</u>
1				Rate Units
2	Primary Raw Value	32-Bit Float	Read	mA
3				
4	Last Calibration Date	32-Bit Integer	Read	Unix Time
5				
6	Flow Total	32-Bit Float	Read	Flow Units
7				
8	Input Filter	32-Bit Float	Read/Write	mA
9				
10	Deadband	32-Bit Float	Read/Write	<u>Flow Units</u>
11				Rate Units
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14	LoLo Alarm Setpoint	32-Bit Float	Read/Write	<u>Flow Units</u>
15				Rate Units
16	Low Alarm Setpoint	32-Bit Float	Read/Write	<u>Flow Units</u>
17				Rate Units
18	High Alarm Setpoint	32-Bit Float	Read/Write	<u>Flow Units</u>
19				Rate Units
20	HiHi Alarm Setpoint	32-Bit Float	Read/Write	<u>Flow Units</u>
21				Rate Units
22	24-Hour Flow Total	32-Bit Float	Read	Flow Units
23				
24				
25	Reset Total Flow	Boolean	Read/Write	Write 1 to Reset Flow Total
26	24-Hour Average Flowrate	32-Bit Float	Read	<u>Flow Units</u>
27				Rate Units
28	Low Alarm	Boolean	Read	1 = Alarm Active
29	High Alarm	Boolean	Read	1 = Alarm Active
30	LoLo Alarm	Boolean	Read	1 = Alarm Active
31	HiHi Alarm	Boolean	Read	1 = Alarm Active
32	Cal Required	Boolean	Read	1 = Alarm Active
33	Input Failure	Boolean	Read	1 = Alarm Active
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.3 Sensor Input Alarm Bitfield

5.3.4 Digital Input Address Maps

5.3.4.1 Digital Input / DI State Type Address Map

Digital Input / DI State Type Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Last Reset Date	32-Bit Integer	Read	Unix Time
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18				
19				
20				
21				
22	24-Hour Time On †	32-Bit Integer	Read	Seconds
23				
24				
25				
26				
27				
28				
29				
30				
31				
32	Reset Total Time	Boolean	Read/Write	Write 1 to Reset Time
33	DI State	Boolean	Read	0 = Open, 1 = Closed
34	Interlock State	Boolean	Read	0 = Inactive 1 = Active Interlock
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.4 Digital Input Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.4.2 Digital Input / Contacting Flow Meter Type Address Map

Digital Input / Contacting Flow Meter Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Last Reset Date	32-Bit Integer	Read	Unix Time
1				
2	Total Flow	32-Bit Float	Read	Flow Units
3				
4				
5				
6	Total Flow Alarm Setpoint	32-Bit Float	Read/Write	0 – 1,000,000,000 Flow Units
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18				
19				
20				
21				
22	24-Hour Flow Total †	32-Bit Float	Read	Flow Units
23				
24				
25				
26				
27				
28				
29				
30				
31				
32	Reset Total Flow	Boolean	Read/Write	Write 1 to Reset Flow Total
33				
34				
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.4 Digital Input Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.4.3 Digital Input / Paddlewheel Flow Meter Type Address Map

Digital Input / Paddlewheel Flow Meter Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Last Reset Date	32-Bit Integer	Read	Unix Time
1				
2	Total Flow	32-Bit Float	Read	Flow Units
3				
4	Current Flowrate	32-Bit Float	Read	<u>Flow Units</u>
5				Rate Units
6	Total Flow Alarm Setpoint	32-Bit Float	Read/Write	0 – 1,000,000,000 Flow Units
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	<u>Flow Units</u>
11				Rate Units
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14				
15				
16	Low Alarm Setpoint	32-Bit Float	Read/Write	<u>Flow Units</u>
17				Rate Units
18	High Alarm Setpoint	32-Bit Float	Read/Write	<u>Flow Units</u>
19				Rate Units
20				
21				
22	24-Hour Flow Total †	32-Bit Float	Read	Flow Units
23				
24	24-Hour Minimum Flowrate †	32-Bit Float	Read	<u>Flow Units</u>
25				Rate Units
26	24-Hour Maximum Flowrate †	32-Bit Float	Read	<u>Flow Units</u>
27				Rate Units
28	24-Hour Average Flowrate †	32-Bit Float	Read	<u>Flow Units</u>
29				Rate Units
30				
31				
32	Reset Total Flow	Boolean	Read/Write	Write 1 to Reset Flow Total
33				
34				
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.4 Digital Input Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.4.4 Digital Input / DI Counter Type Address Map

Digital Input / DI Counter Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Last Reset Date	32-Bit Integer	Read	Unix Time
1				
2	Total	32-Bit Float	Read	Units
3				
4	Current Rate	32-Bit Float	Read	<u>Units</u> Rate Units
5				
6	Total Alarm Setpoint	32-Bit Float	Read/Write	0 – 1,000,000,000 Units
7				
8				
9				
10				
11				
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14				
15				
16				
17				
18				
19				
20				
21				
22	24-Hour Total †	32-Bit Float	Read	Units
23				
24	24-Hour Minimum Rate †	32-Bit Float	Read	<u>Units</u> Rate Units
25				
26	24-Hour Maximum Rate †	32-Bit Float	Read	<u>Units</u> Rate Units
27				
28	24-Hour Average Rate †	32-Bit Float	Read	<u>Units</u> Rate Units
29				
30				
31				
32	Reset Total	Boolean	Read/Write	Write 1 to Reset Total
33				
34				
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.4 Digital Input Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.4.5 Digital Input / Flow Monitor Type Address Map

Digital Input / Flow Monitor Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Last Reset Date	32-Bit Integer	Read	Unix Time
1				
2	Total Feed	32-Bit Float	Read	Flow Units
3				
4	Current Flowrate	32-Bit Float	Read	<u>Flow Units</u> Rate Units
5				
6	Totalizer Alarm Setpoint	32-Bit Float	Read/Write	0 – 1,000,000 Flow Units
7				
8	Volume/Contact	32-Bit Float	Read/Write	0.001 – 1000.000 Flow Units / Pulse
9				
10				
11				
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14	Reprime Time	16-Bit Integer	Read/Write	0 – 3599 Seconds
15	Flow Alarm Delay	16-Bit Integer	Read/Write	10 – 3599 Seconds
16	Flow Alarm Clear	32-Bit Float	Read/Write	1 – 100,000 Pulses
17				
18				
19				
20				
21				
22	24-Hour Flow Total †	32-Bit Float	Read	Flow Units
23				
24	24-Hour Minimum Flowrate †	32-Bit Float	Read	<u>Flow Units</u> Rate Units
25				
26	24-Hour Maximum Flowrate †	32-Bit Float	Read	<u>Flow Units</u> Rate Units
27				
28	24-Hour Average Flowrate †	32-Bit Float	Read	<u>Flow Units</u> Rate Units
29				
30				
31				
32	Reset Total Flow	Boolean	Read/Write	Write 1 to Reset Flow Total
33				
34				
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.4 Digital Input Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.4.6 Digital Input / Remote Modbus Type Address Map

Digital Input / Remote Modbus Type Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Last Reset Date	32-Bit Integer	Read	Unix Time
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18				
19				
20				
21				
22	24-Hour Time On	32-Bit Integer	Read	Seconds
23				
24				
25				
26				
27				
28				
29				
30				
31				
32	Reset Total Time	Boolean	Read/Write	Write 1 to Reset Time
33	DI State	Boolean	Read/Write	0 = Open, 1 = Closed
34	Interlock State	Boolean	Read	0 = Inactive 1 = Active Interlock
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.4 Digital Input Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.5 Virtual Input Address Maps

5.3.5.1 Virtual Input / Calculation Type Address Map

Virtual Input / Calculation Type Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Primary Value	32-Bit Float	Read	Virtual Input Units
1				
2				
3				
4				
5				
6				
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Virtual Input Units
11				
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14	LoLo Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
15				
16	Low Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
17				
18	High Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
19				
20	HiHi Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
21				
22	24-Hour Minimum †	32-Bit Float	Read	Virtual Input Units
23				
24	24-Hour Maximum †	32-Bit Float	Read	Virtual Input Units
25				
26	24-Hour Average †	32-Bit Float	Read	Virtual Input Units
27				
28	Low Alarm	Boolean	Read	1 = Alarm Active
29	High Alarm	Boolean	Read	1 = Alarm Active
30	LoLo Alarm	Boolean	Read	1 = Alarm Active
31	HiHi Alarm	Boolean	Read	1 = Alarm Active
32				
33	Misc. Alarm	Boolean	Read	1 = Out-Of-Range or Input Failure Alarm Active
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.5 Virtual Input Alarm Bitfield

† Field is only available for EP1000 and EP2100 Controllers.

5.3.5.2 Virtual Input / Raw Value Type Address Map

Virtual Input / Raw Value Type Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Primary Value	32-Bit Float	Read	Virtual Input Units
1				
2				
3				
4				
5				
6				
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Virtual Input Units
11				
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14	LoLo Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
15				
16	Low Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
17				
18	High Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
19				
20	HiHi Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
21				
22	24-Hour Minimum †	32-Bit Float	Read	Virtual Input Units
23				
24	24-Hour Maximum †	32-Bit Float	Read	Virtual Input Units
25				
26	24-Hour Average †	32-Bit Float	Read	Virtual Input Units
27				
28	Low Alarm	Boolean	Read	1 = Alarm Active
29	High Alarm	Boolean	Read	1 = Alarm Active
30	LoLo Alarm	Boolean	Read	1 = Alarm Active
31	HiHi Alarm	Boolean	Read	1 = Alarm Active
32				
33	Misc. Alarm	Boolean	Read	1 = Out-Of-Range or Input Failure Alarm Active
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.5 Virtual Input Alarm Bitfield

† Field is only available for EP1000 and EP2100 Controllers.

5.3.5.3 Virtual Input / Redundant Sensor Type Address Map

Virtual Input / Redundant Sensor Type Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Primary Value	32-Bit Float	Read	Virtual Input Units
1				
2				
3				
4				
5				
6				
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Virtual Input Units
11				
12				
13				
14				
15				
16				
17				
18	Deviation Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
19				
20				
21				
22	24-Hour Minimum	32-Bit Float	Read	Virtual Input Units
23				
24	24-Hour Maximum	32-Bit Float	Read	Virtual Input Units
25				
26	24-Hour Average	32-Bit Float	Read	Virtual Input Units
27				
28				
29				
30				
31				
32	Deviation Alarm	Boolean	Read	1 = Alarm Active
33	Misc. Alarm	Boolean	Read	1 = Input Failure Alarm Active
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.5 Virtual Input Alarm Bitfield

5.3.5.4 Virtual Input / Disturbance Type Address Map

Virtual Input / Disturbance Type Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Primary Value	32-Bit Float	Read	Unitless
1				
2				
3				
4				
5				
6	Value at Minimum Disturbance	32-Bit Float	Read/Write	Unitless
7				
8	Value at Maximum Disturbance	32-Bit Float	Read/Write	Unitless
9				
10				
11				
12	Smoothing Factor	32-Bit Float	Read/Write	0 – 90%
13				
14				
15				
16				
17				
18				
19				
20				
21				
22	Minimum Disturbance	32-Bit Float	Read/Write	Disturbance Input Units
23				
24	Maximum Disturbance	32-Bit Float	Read/Write	Disturbance Input Units
25				
26	24-Hour Minimum	32-Bit Float	Read	Unitless
27				
28	24-Hour Maximum	32-Bit Float	Read	Unitless
29				
30	24-Hour Average	32-Bit Float	Read	Unitless
31				
32				
33				
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.5 Virtual Input Alarm Bitfield

5.3.5.5 Virtual Input / Remote Modbus Type Address Map

Virtual Input / Remote Modbus Type Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Primary Value	32-Bit Float	Read/Write	Virtual Input Units
1				
2				
3				
4				
5				
6				
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Virtual Input Units
11				
12				
13				
14	LoLo Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
15				
16	Low Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
17				
18	High Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
19				
20	HiHi Alarm Setpoint	32-Bit Float	Read/Write	Virtual Input Units
21				
22	24-Hour Minimum	32-Bit Float	Read	Virtual Input Units
23				
24	24-Hour Maximum	32-Bit Float	Read	Virtual Input Units
25				
26	24-Hour Average	32-Bit Float	Read	Virtual Input Units
27				
28	Low Alarm	Boolean	Read	1 = Alarm Active
29	High Alarm	Boolean	Read	1 = Alarm Active
30	LoLo Alarm	Boolean	Read	1 = Alarm Active
31	HiHi Alarm	Boolean	Read	1 = Alarm Active
32				
33	Misc. Alarm	Boolean	Read	1 = Out-Of-Range or Message Error or Update Timeout or Input Failure Alarm Active
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.5 Virtual Input Alarm Bitfield

5.3.6 Relay Output Address Maps

5.3.6.1 Relay Output / Manual Control Mode Address Map

Relay Output / Manual Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22				
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30				
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.2 Relay Output / On/Off Control Mode Address Map

Relay Output / On/Off Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Duty Cycle	32-Bit Float	Read/Write	0 – 100%
13				
14	Duty Cycle Period	16-Bit Integer	Read/Write	0 – 3599 Seconds
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.3 Relay Output / On/Off Disturbance Control Mode Address Map

Relay Output / On/Off Disturbance Control Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Duty Cycle	32-Bit Float	Read/Write	0 – 100%
13				
14	Duty Cycle Period	16-Bit Integer	Read/Write	0 – 3599 Seconds
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On	32-Bit Integer	Read	Seconds
25				
26	Daily Maximum Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.4 Relay Output / Dual Setpoint Control Mode Address Map

Relay Output / Dual Setpoint Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6	Setpoint 1	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Setpoint 2	32-Bit Float	Read/Write	Input Sensor Units
9				
10	Deadband	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Duty Cycle	32-Bit Float	Read/Write	0 – 100%
13				
14	Duty Cycle Period	16-Bit Integer	Read/Write	0 – 3599 Seconds
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.5 Relay Output / Time Proportional Control Mode Address Map

Relay Output / Time Proportional Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Proportional Band	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Current Cycle	32-Bit Float	Read	Seconds
13				
14	Sample Period	32-Bit Integer	Read/Write	10 – 86,399 Seconds
15				
16				
17				
18				
19				
20				
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.6 Relay Output / Intermittent Sampling Control Mode Address Map

Relay Output / Intermittent Sampling Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Proportional Band	32-Bit Float	Read/Write	Input Sensor Units
11				
12				
13				
14	Sample Time	16-Bit Integer	Read/Write	10 – 3599 Seconds
15	Hold Time	16-Bit Integer	Read/Write	10 – 3599 Seconds
16	Max Blowdown	32-Bit Integer	Read/Write	0 – 86,399 Seconds
17				
18	Wait Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20				
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.7 Relay Output / Bleed And Feed Control Mode Address Map

Relay Output / Bleed And Feed Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20				
21				
22	Feed Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Feed Timeout	Boolean	Read/Write	Write 1 to Reset Feed Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.8 Relay Output / Bleed Then Feed Control Mode Address Map

Relay Output / Bleed Then Feed Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Feed Time	32-Bit Integer	Read	Seconds
5				
6	Bleed Time	32-Bit Integer	Read	Seconds
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Feed Percentage	32-Bit Float	Read/Write	0 – 100%
21				
22	Feed Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Feed Timeout	Boolean	Read/Write	Write 1 to Reset Feed Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.9 Relay Output / Flow Timer Control Mode Address Map

Relay Output / Flow Timer Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Feed Time	32-Bit Integer	Read	Seconds
5				
6	Accumulator Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Volume Units
7				
8	Accumulator Total	32-Bit Float	Read	Volume Units
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Feed Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.10 Relay Output / Counter Timer Control Mode Address Map

Relay Output / Counter Timer Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Feed Time	32-Bit Integer	Read	Seconds
5				
6	Accumulator Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Units
7				
8	Accumulator Total	32-Bit Float	Read	Units
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Feed Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.11 Relay Output / Target PPM Control Mode Address Map

Relay Output / Target PPM Control Mode Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Feed Time	32-Bit Integer	Read	Seconds
5				
6	Accumulator Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Volume Units
7				
8	Accumulator Total	32-Bit Float	Read	Volume Units
9				
10	Target PPM	32-Bit Float	Read/Write	1 – 1,000,000 ppm
11				
12	Daily Maximum Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
13				
14	24-Hour Time On	32-Bit Integer	Read	Seconds
15				
16	Specific Gravity Of Product	32-Bit Float	Read/Write	0 – 9.999 mg/l
17				
18	Pump Capacity	32-Bit Float	Read/Write	0 – 10,000 <u>Volume Units</u> Hour
19				
20	Pump Setting	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Low Cycles Limit	32-Bit Float	Read/Write	0.00 – 100.00
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.12 Relay Output / PPM By Volume Control Mode Address Map

Relay Output / PPM By Volume Control Mode Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Feed Volume	32-Bit Float	Read	Volume Units
5				
6	Accumulator Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Volume Units
7				
8	Accumulator Total	32-Bit Float	Read	Volume Units
9				
10	Target PPM	32-Bit Float	Read/Write	1 – 1,000,000 ppm
11				
12	Daily Maximum Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
13				
14				
15				
16	Specific Gravity Of Product	32-Bit Float	Read/Write	0 – 9.999 mg/l
17				
18				
19				
20	24-Hour Time On	32-Bit Integer	Read	Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Low Cycles Limit	32-Bit Float	Read/Write	0.00 – 100.00
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.13 Relay Output / Flow Meter Ratio Control Mode Address Map

Relay Output / Flow Meter Ratio Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Volume	32-Bit Float	Read	Flow Units
5				
6	Accumulator Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Flow Units
7				
8	Accumulator Total	32-Bit Float	Read	Flow Units
9				
10	Bleed Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Flow Units
11				
12	Bleed Cycle Volume	32-Bit Float	Read	Flow Units
13				
14				
15				
16				
17				
18				
19				
20	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.14 Relay Output / Volumetric Blend Control Mode Address Map

Relay Output / Volumetric Blend Control Mode Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Remaining Volume	32-Bit Float	Read	Flow Units
5				
6	Accumulator Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Flow Units
7				
8	Cycle Volume	32-Bit Float	Read	Flow Units
9				
10	Bleed Volume Setpoint	32-Bit Float	Read/Write	1 – 1,000,000 Flow Units
11				
12				
13				
14				
15				
16				
17				
18				
19				
20	Daily Maximum Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On	32-Bit Integer	Read	Seconds
25				
26				
27	Reset Timer	Boolean	Read/Write	Write 1 to Reset Feed Timer
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

Relay Output / Dual Switch Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26	Daily Maximum Time Limit †	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

Relay Output / Boolean Logic Control Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On	32-Bit Integer	Read	Seconds
25				
26	Daily Maximum Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.17 Relay Output / Percent Timer Control Mode Address Map

Relay Output / Percent Timer Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18				
19				
20	Feed Percentage	32-Bit Float	Read/Write	0 – 100%
21				
22	Feed Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30				
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.6.18 Relay Output / Event Timer Control Mode Address Map

Relay Output / Event Timer Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6				
7				
8	Event 5 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
9				
10	Event 5 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
11				
12	Event 4 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
13				
14	Event 4 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
15				
16	Event 3 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
17				
18	Event 3 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Event 2 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
21				
22	Event 2 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Event 1 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
25				
26	Event 1 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Active Timer Event	16-Bit Integer	Read	Event Number
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.19 Relay Output / Biocide Timer Control Mode Address Map

Relay Output / Biocide Timer Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6	Bleed Lockout	32-Bit Integer	Read/Write	0 – 86,399 Seconds
7				
8	Prebleed To Setpoint	32-Bit Float	Read/Write	Input Sensor Units
9				
10	Prebleed Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds
11				
12	Event 4 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
13				
14	Event 4 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
15				
16	Event 3 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
17				
18	Event 3 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Event 2 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
21				
22	Event 2 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Event 1 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
25				
26	Event 1 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Active Timer Event	16-Bit Integer	Read	Event Number
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.20 Relay Output / Spike Control Mode Address Map

Relay Output / Spike Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Spike Event Time	32-Bit Integer	Read	Seconds
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Spike Setpoint	32-Bit Float	Read/Write	Input Sensor Units
9				
10	Deadband	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Duty Cycle	32-Bit Float	Read/Write	0 – 100%
13				
14	Duty Cycle Period	16-Bit Integer	Read/Write	0 – 3599 Seconds
15				
16	Event 3 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
17				
18	Event 3 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Event 2 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
21				
22	Event 2 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Event 1 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
25				
26	Event 1 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Active Timer Event	16-Bit Integer	Read	Event Number
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.21 Relay Output / Probe Wash Control Mode Address Map

Relay Output / Probe Wash Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Cycle Time	32-Bit Integer	Read	Seconds
5				
6	Hold Time Limit	32-Bit Integer	Read/Write	0 – 3599 Seconds
7				
8	Event 5 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
9				
10	Event 5 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
11				
12	Event 4 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
13				
14	Event 4 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
15				
16	Event 3 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
17				
18	Event 3 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Event 2 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
21				
22	Event 2 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Event 1 Start Time	32-Bit Integer	Read/Write	0 – 86,399 Seconds Since Midnight
25				
26	Event 1 Duration	32-Bit Integer	Read/Write	0 – 86,399 Seconds
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Active Timer Event	16-Bit Integer	Read	Event Number
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.22 Relay Output / Plating Control Mode Address Map

Relay Output / Plating Control Address Map (EP1000 and EP200N Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Total Feed Volume	32-Bit Float	Read	Volume Units
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Deadband	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Duty Cycle	32-Bit Float	Read/Write	0 – 100%
13				
14	Duty Cycle Period	16-Bit Integer	Read/Write	0 – 3599 Seconds
15				
16	Pump Setting	32-Bit Float	Read/Write	0 – 100%
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Total Turns	32-Bit Float	Read	Turns
25				
26	Turnover Limit	32-Bit Float	Read/Write	0 – 100 Turns
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Total	Boolean	Read/Write	Write 1 to Reset Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.23 Relay Output / Plating Follow Control Mode Address Map

Relay Output / Plating Follow Control Address Map (EP200 and EP200N Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Total Feed Volume	32-Bit Float	Read	Volume Units
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18				
19				
20				
21				
22				
23				
24				
25				
26				
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30				
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.6.24 Relay Output / Lag Output Control Mode Address Map

Relay Output / Lag Output Address Map				
Address	Field	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6	Setpoint 1 §	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Setpoint 2 §	32-Bit Float	Read/Write	Input Sensor Units
9				
10	Deadband §	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Activation Delay Time ‡§	32-Bit Integer	Read/Write	0 – 86,399 Seconds
13				
14	Wear Level Cycle Time ‡§	32-Bit Integer	Read/Write	10 – 86,399 Seconds
15				
16	Current Activation Time ‡§	32-Bit Integer	Read	Seconds
17				
18	Current Wear Level Cycle Time ‡§	32-Bit Integer	Read	Seconds
19				
20	No. of Activated Outputs ‡§	16-Bit Integer	Read	Count
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24				
25				
26	24-Hour Time On †	32-Bit Integer	Read	Seconds
27				
28				
29				
30	Reset Output TO	Boolean	Read/Write	Write 1 to Reset Output Timeout
31	Relay State	Boolean	Read	1 = Relay On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

‡ Field is only defined for Lag Outputs configured as the “Last Lag” in the chain.

§ Field is only meaningful for certain configurations of Lead-Lag chains.

Relay Output / Alarm Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4				
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22				
23				
24	24-Hour Time On †	32-Bit Integer	Read	Seconds
25				
26				
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30				
31	Relay State	Boolean	Read	0 = Off, 1 = On
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Integer	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.7 Pulse Relay Output Address Maps

5.3.7.1 Pulse Relay Output / Manual Control Mode Address Map

Pulse Relay Output / Manual Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18	On Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
19				
20	Off Time Delay	32-Bit Integer	Read/Write	0 – 86,399 Seconds
21				
22				
23				
24	24-Hour Average Output †	32-Bit Float	Read	Percent
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30				
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.7.2 Pulse Relay Output / Pulse Proportional Control Mode Address Map

Pulse Relay Output / Pulse Proportional Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Proportional Band	32-Bit Float	Read/Write	Input Sensor Units
11				
12				
13				
14				
15				
16	24-Hour Average Output †	32-Bit Float	Read	Percent
17				
18	Minimum Output	32-Bit Float	Read/Write	0 – 100%
19				
20	Maximum Output	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24				
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.7.3 Pulse Relay Output / Flow Proportional Control Mode Address Map

Pulse Relay Output / Flow Proportional Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Target PPM	32-Bit Float	Read/Write	1 – 1,000,000 ppm
7				
8				
9				
10				
11				
12				
13				
14	24-Hour Average Output †	32-Bit Float	Read	Percent
15				
16	Specific Gravity Of Product	32-Bit Float	Read/Write	0 – 9.999 mg/l
17				
18	Pump Capacity	32-Bit Float	Read/Write	0 – 10,000 <u>Volume Units</u> Hour
19				
20	Pump Setting	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Low Cycles Limit	32-Bit Float	Read/Write	0.00 – 100.00
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.7.4 Pulse Relay Output / Pulse PID Control Mode Address Map

Pulse Relay Output / Pulse PID Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Current Integral	32-Bit Float	Read	Seconds
9				
10	Gain or Proportional Gain ‡	32-Bit Float	Read/Write	0.001 – 1000
11				
12	Integral Time or Integral Gain ‡	32-Bit Float	Read/Write	0.001 – 1000
13				
14	Derivative Time or Derivative Gain ‡	32-Bit Float	Read/Write	0 – 1000
15				
16	24-Hour Average Output †	32-Bit Float	Read	Percent
17				
18	Minimum Output	32-Bit Float	Read/Write	0 – 100%
19				
20	Maximum Output	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 seconds
23				
24				
25	Reset PID Integral	Boolean	Read/Write	Write 1 to Reset PID Integral
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

‡ Setting is dependent on current selection for “PID Gain Form” (see Controller Instruction Manual)

5.3.7.5 Pulse Relay Output / Pulse Disturbance Control Mode Address Map

Pulse Relay Output / Pulse Disturbance Control Mode Address Map (EP1000 / EP2100 Controller Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16	24-Hour Average Output	32-Bit Float	Read	Percent
17				
18	Minimum Output	32-Bit Float	Read/Write	0 – 100%
19				
20	Maximum Output	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24				
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.7.6 Pulse Relay Output / Lag Output Control Mode Address Map

Pulse Relay Output / Lag Output Control Mode Address Map				
Address	Field	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Percent Output	32-Bit Float	Read	Percent
5				
6	Setpoint 1 §	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Setpoint 2 §	32-Bit Float	Read/Write	Input Sensor Units
9				
10	Deadband §	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Activation Delay Time ‡§	32-Bit Integer	Read/Write	0 – 86,399 Seconds
13				
14	Wear Level Cycle Time ‡§	32-Bit Integer	Read/Write	10 – 86,399 Seconds
15				
16	Current Activation Time ‡§	32-Bit Integer	Read	Seconds
17				
18	Current Wear Level Cycle Time ‡§	32-Bit Integer	Read	Seconds
19				
20	No. of Activated Outputs ‡§	16-Bit Integer	Read	Count
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Average Output †	32-Bit Float	Read	Percent
25				
26				
27				
28				
29				
30	Reset Output TO	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.6 Relay Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

‡ Field is only defined for Lag Outputs configured as the “Last Lag” in the chain.

§ Field is only meaningful for certain configurations of Lead-Lag chains.

5.3.8 Analog Output Address Maps

5.3.8.1 Analog Output / Manual Control Mode Address Map

Analog Output / Manual Control Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16	24-Hour Average Output †	32-Bit Float	Read	Percent
17				
18				
19				
20				
21				
22				
23				
24				
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30				
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.8.2 Analog Output / Retransmit Mode Address Map

Analog Output / Retransmit Mode Address Map							
Address	Name	Data Encoding	Permissions	Value			
0	Time On	32-Bit Integer	Read	Seconds			
1							
2	Total Time	32-Bit Integer	Read	Seconds			
3							
4	Output	32-Bit Float	Read	Percent			
5							
6							
7							
8							
9							
10							
11							
12							
13							
14							
15							
16	24-Hour Average Output †	32-Bit Float	Read	Percent			
17							
18							
19							
20							
21							
22							
23							
24							
25							
26	Hand Output	32-Bit Float	Read/Write	0 – 100%			
27							
28							
29							
30							
31							
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total			
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode			
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes			
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active			

† Field is only available for EP1000 and EP2100 Controllers.

5.3.8.3 Analog Output / Proportional Control Mode Address Map

Analog Output / Proportional Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8				
9				
10	Proportional Band	32-Bit Float	Read/Write	Input Sensor Units
11				
12				
13				
14				
15				
16	24-Hour Average Output †	32-Bit Float	Read	Percent
17				
18	Minimum Output	32-Bit Float	Read/Write	0 – 100%
19				
20	Maximum Output	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24				
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.8.4 Analog Output / Flow Proportional Control Mode Address Map

Analog Output / Flow Proportional Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Target PPM	32-Bit Float	Read/Write	1 – 1,000,000 ppm
7				
8				
9				
10				
11				
12				
13				
14	24-Hour Average Output †	32-Bit Float	Read	Percent
15				
16	Specific Gravity Of Product	32-Bit Float	Read/Write	0 – 9.999 mg/l
17				
18	Pump Capacity	32-Bit Float	Read/Write	0 – 10,000 <u>Volume Units</u> Hour
19				
20	Pump Setting	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	Low Cycles Limit	32-Bit Float	Read/Write	0.00 – 100.00
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

5.3.8.5 Analog Output / PID Control Mode Address Map

Analog Output / PID Control Mode Address Map				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Setpoint	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Current Integral	32-Bit Float	Read	Seconds
9				
10	Gain or Proportional Gain ‡	32-Bit Float	Read/Write	0.001 – 1000
11				
12	Integral Time or Integral Gain ‡	32-Bit Float	Read/Write	0.001 – 1000
13				
14	Derivative Time or Derivative Gain ‡	32-Bit Float	Read/Write	0 – 1000
15				
16	24-Hour Average Output †	32-Bit Float	Read	Percent
17				
18	Minimum Output	32-Bit Float	Read/Write	0 – 100%
19				
20	Maximum Output	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 seconds
23				
24				
25	Reset PID Integral	Boolean	Read/Write	Write 1 to Reset PID Integral
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

‡ Setting is dependent on current selection for “PID Gain Form” (see Controller Instruction Manual)

5.3.8.6 Analog Output / Disturbance Control Mode Address Map

Analog Output / Disturbance Control Mode Address Map (EP1000 and EP2100 Controllers Only)				
Address	Name	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16	24-Hour Average Output	32-Bit Float	Read	Percent
17				
18	Minimum Output	32-Bit Float	Read/Write	0 – 100%
19				
20	Maximum Output	32-Bit Float	Read/Write	0 – 100%
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24				
25				
26	Hand Output	32-Bit Float	Read/Write	0 – 100%
27				
28	Hand Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
29				
30	Reset Output Timeout	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

5.3.8.7 Analog Output / Lag Output Control Mode Address Map

Analog Output / Lag Output Control Mode Address Map				
Address	Field	Data Encoding	Permissions	Value
0	Time On	32-Bit Integer	Read	Seconds
1				
2	Total Time	32-Bit Integer	Read	Seconds
3				
4	Output	32-Bit Float	Read	Percent
5				
6	Setpoint 1 §	32-Bit Float	Read/Write	Input Sensor Units
7				
8	Setpoint 2 §	32-Bit Float	Read/Write	Input Sensor Units
9				
10	Deadband §	32-Bit Float	Read/Write	Input Sensor Units
11				
12	Activation Delay Time ‡§	32-Bit Integer	Read/Write	0 – 86,399 Seconds
13				
14	Wear Level Cycle Time ‡§	32-Bit Integer	Read/Write	10 – 86,399 Seconds
15				
16	Current Activation Time ‡§	32-Bit Integer	Read	Seconds
17				
18	Current Wear Level Cycle Time ‡§	32-Bit Integer	Read	Seconds
19				
20	No. of Activated Outputs ‡§	16-Bit Integer	Read	Count
21				
22	Output Time Limit	32-Bit Integer	Read/Write	0 – 86,399 Seconds
23				
24	24-Hour Average Output †	32-Bit Float	Read	Percent
25				
26				
27				
28				
29				
30	Reset Output TO	Boolean	Read/Write	Write 1 to Reset Output Timeout
31				
32	Reset Time Total	Boolean	Read/Write	Write 1 to Reset Time Total
33	HOA Setting	16-Bit Integer	Read/Write	0 = Hand, 1 = Off, 2 = Auto Mode
34	Status	16-Bit Status	Read	See 5.4 Status Register Codes
35	Alarm Bitfield	16-Bit Bitfield	Read	See 5.5.7 Analog Output Alarm Bitfield When accessed as a Coil, Returns 1 if any alarm is active

† Field is only available for EP1000 and EP2100 Controllers.

‡ Field is only defined for Lag Outputs configured as the “Last Lag” in the chain.

§ Field is only meaningful for certain configurations of Lead-Lag chains.

5.3.9 Alternate Address Maps

5.3.9.1 Alternate Sensor Input Address Map

Alternate Sensor Input Address Map								
Object	Primary Value	Status	Alarm Bitfield	Low Alarm	High Alarm	LoLo Alarm	HiHi Alarm	Cal Required
Data Encoding	32-Bit Float	16-Bit Status	16-Bit Bitfield	Boolean	Boolean	Boolean	Boolean	Boolean
Permissions	Read	Read	Read	Read	Read	Read	Read	Read
Value	Sensor Units	See 5.4 Status Register Codes	See 5.5.3 Sensor Input Alarm Bitfield	1 = Alarm Active	1 = Alarm Active	1 = Alarm Active	1 = Alarm Active	1 = Alarm Active
Sensor Number	Address	Address	Address	Address	Address	Address	Address	Address
Sensor 1	x9217	x9281	x9313	x9345	x9377	x9409	x9441	x9473
Sensor 2	x9219	x9282	x9314	x9346	x9378	x9410	x9442	x9474
Sensor 3	x9221	x9283	x9315	x9347	x9379	x9411	x9443	x9475
Sensor 4	x9223	x9284	x9316	x9348	x9380	x9412	x9444	x9476
Sensor 5	x9225	x9285	x9317	x9349	x9381	x9413	x9445	x9477
Sensor 6	x9227	x9286	x9318	x9350	x9382	x9414	x9446	x9478
Sensor 7	x9229	x9287	x9319	x9351	x9383	x9415	x9447	x9479
Sensor 8	x9231	x9288	x9320	x9352	x9384	x9416	x9448	x9480
Sensor 9	x9233	x9289	x9321	x9353	x9385	x9417	x9449	x9481
Sensor 10	x9235	x9290	x9322	x9354	x9386	x9418	x9450	x9482
Sensor 11	x9237	x9291	x9323	x9355	x9387	x9419	x9451	x9483
Sensor 12	x9239	x9292	x9324	x9356	x9388	x9420	x9452	x9484
Sensor 13	x9241	x9293	x9325	x9357	x9389	x9421	x9453	x9485
Sensor 14	x9243	x9294	x9326	x9358	x9390	x9422	x9454	x9486
Sensor 15	x9245	x9295	x9327	x9359	x9391	x9423	x9455	x9487
Sensor 16	x9247	x9296	x9328	x9360	x9392	x9424	x9456	x9488

Alternate Sensor Input Address Map								
Object	Primary Value	Status	Alarm Bitfield	Low Alarm	High Alarm	LoLo Alarm	HiHi Alarm	Cal Required
Data Encoding	32-Bit Float	16-Bit Status	16-Bit Bitfield	Boolean	Boolean	Boolean	Boolean	Boolean
Permissions	Read	Read	Read	Read	Read	Read	Read	Read
Value	Sensor Units	See 5.4 Status Register Codes	See 5.5.3 Sensor Input Alarm Bitfield	1 = Alarm Active	1 = Alarm Active	1 = Alarm Active	1 = Alarm Active	1 = Alarm Active
Sensor Number	Address	Address	Address	Address	Address	Address	Address	Address
Sensor 17	x9249	x9297	x9329	x9361	x9393	x9425	x9457	x9489
Sensor 18	x9251	x9298	x9330	x9362	x9394	x9426	x9458	x9490
Sensor 19	x9253	x9299	x9331	x9363	x9395	x9427	x9459	x9491
Sensor 20	x9255	x9300	x9332	x9364	x9396	x9428	x9460	x9492
Sensor 21	x9257	x9301	x9333	x9365	x9397	x9429	x9461	x9493
Sensor 22	x9259	x9302	x9334	x9366	x9398	x9430	x9462	x9494
Sensor 23	x9261	x9303	x9335	x9367	x9399	x9431	x9463	x9495
Sensor 24	x9263	x9304	x9336	x9368	x9400	x9432	x9464	x9496
Sensor 25	x9265	x9305	x9337	x9369	x9401	x9433	x9465	x9497
Sensor 26	x9267	x9306	x9338	x9370	x9402	x9434	x9466	x9498
Sensor 27	x9269	x9307	x9339	x9371	x9403	x9435	x9467	x9499
Sensor 28	x9271	x9308	x9340	x9372	x9404	x9436	x9468	x9500
Sensor 29	x9273	x9309	x9341	x9373	x9405	x9437	x9469	x9501
Sensor 30	x9275	x9310	x9342	x9374	x9406	x9438	x9470	x9502
Sensor 31	x9277	x9311	x9343	x9375	x9407	x9439	x9471	x9503
Sensor 32	x9278	x9312	x9344	x9376	x9408	x9440	x9472	x9504

5.3.9.2 Alternate Digital Input Address Map

Object	DI State	Interlock State	Total Time	Flowrate	Flow Total	Alarm Bitfield
Data Encoding	Boolean	Boolean	32-Bit Integer	32-Bit Float	32-Bit Float	16-Bit Bitfield
Permissions	Read	Read	Read	Read	Read	Read
Control Modes	DI State	DI State	DI State	Paddlewheel FM Feed Monitor	Contacting FM Paddlewheel FM Feed Monitor	All
Value	0 = Open 1 = Closed	0 = Inactive 1 = Active Interlock	Seconds	Flow Units Rate Units	Flow Units	See 5.5.4 Digital Input Alarm Bitfield
Digital Input Number	Address	Address	Address	Address	Address	Address
Digital Input 1	x9681	x9697	x9649	x9617	x9649	x9713
Digital Input 2	x9682	x9698	x9651	x9619	x9651	x9714
Digital Input 3	x9683	x9699	x9653	x9621	x9653	x9715
Digital Input 4	x9684	x9700	x9655	x9623	x9655	x9716
Digital Input 5	x9685	x9701	x9657	x9625	x9657	x9717
Digital Input 6	x9686	x9702	x9659	x9627	x9659	x9718
Digital Input 7	x9687	x9703	x9661	x9629	x9661	x9719
Digital Input 8	x9688	x9704	x9663	x9631	x9663	x9720
Digital Input 9	x9689	x9705	x9665	x9633	x9665	x9721
Digital Input 10	x9690	x9706	x9667	x9635	x9667	x9722
Digital Input 11	x9691	x9707	x9669	x9637	x9669	x9723
Digital Input 12	x9692	x9708	x9671	x9639	x9671	x9724
Digital Input 13	x9693	x9709	x9673	x9641	x9665	x9725
Digital Input 14	x9694	x9710	x9675	x9643	x9667	x9726
Digital Input 15	x9695	x9711	x9677	x9645	x9669	x9727
Digital Input 16	x9696	x9712	x9679	x9647	x9671	x9728

5.3.9.3 Alternate Virtual Input Address Map

Alternate Virtual Input Address Map			
Object	Primary Value	Status	Alarm Bitfield
Data Encoding	32-Bit Float	16-Bit Status	16-Bit Bitfield
Permissions	Read	Read	Read
Value	Virtual Input Units	See 5.4 Status Register Codes	See 5.5.5 Virtual Input Alarm Bitfield
Virtual Input Number	Address	Address	Address
Virtual Input 1	x9505	x9537	x9553
Virtual Input 2	x9507	x9538	x9554
Virtual Input 3	x9509	x9539	x9555
Virtual Input 4	x9511	x9540	x9556
Virtual Input 5	x9513	x9541	x9557
Virtual Input 6	x9515	x9542	x9558
Virtual Input 7	x9517	x9543	x9559
Virtual Input 8	x9519	x9544	x9560
Virtual Input 9	x9521	x9545	x9561
Virtual Input 10	x9523	x9546	x9562
Virtual Input 11	x9525	x9547	x9563
Virtual Input 12	x9527	x9548	x9564
Virtual Input 13	x9529	x9549	x9565
Virtual Input 14	x9531	x9550	x9566
Virtual Input 15	x9533	x9551	x9567
Virtual Input 16	x9535	x9552	x9568

5.3.9.4 Alternate Relay Output Address Map

Object	Relay State	Pulse Output	Time On	Status	Alarm Bitfield
Data Encoding	Boolean	32-Bit Float	32-Bit Integer	16-Bit Status	16-Bit Bitfield
Permissions	Read	Read	Read	Read	Read
Control Modes	All except Pulse Outputs	Only Pulse Outputs	All	All	All
Value	0 = Off 1 = On	%	Seconds	See 5.4 Status Register Codes	See 5.5.6 Relay Alarm Bitfield
Relay Number	Address	Address	Address	Address	Address
Relay 1	x9601	x9793	x9729	x9761	x9777
Relay 2	x9602	x9795	x9731	x9762	x9778
Relay 3	x9603	x9797	x9733	x9763	x9779
Relay 4	x9604	x9799	x9735	x9764	x9780
Relay 5	x9605	x9801	x9737	x9765	x9781
Relay 6	x9606	x9803	x9739	x9766	x9782
Relay 7	x9607	x9805	x9741	x9767	x9783
Relay 8	x9608	x9807	x9743	x9768	x9784
Relay 9	x9609	x9809	x9745	x9769	x9785
Relay 10	x9610	x9811	x9747	x9770	x9786
Relay 11	x9611	x9813	x9749	x9771	x9787
Relay 12	x9612	x9815	x9751	x9772	x9788
Relay 13	x9613	x9817	x9753	x9773	x9789
Relay 14	x9614	x9819	x9755	x9774	x9790
Relay 15	x9615	x9821	x9757	x9775	x9791
Relay 16	x9616	x9823	x9759	x9776	x9792

5.3.9.5 Alternate Analog Output Address Map

Object	Analog Output	Time On	Status	Alarm Bitfield
Data Encoding	32-Bit Float	32-Bit Integer	16-Bit Status	16-Bit Bitfield
Permissions	Read	Read	Read	Read
Value	%	Seconds	See 5.4 Status Register Codes	See 5.5.7 Analog Output Alarm Bitfield
Analog Output Number	Address	Address	Address	Address
Analog Output 1	x9825	x9857	x9921	x9953
Analog Output 2	x9827	x9859	x9922	x9954
Analog Output 3	x9829	x9861	x9923	x9955
Analog Output 4	x9831	x9863	x9924	x9956
Analog Output 5	x9833	x9865	x9925	x9957
Analog Output 6	x9835	x9867	x9926	x9958
Analog Output 7	x9837	x9869	x9927	x9959
Analog Output 8	x9839	x9871	x9928	x9960
Analog Output 9	x9841	x9873	x9929	x9961
Analog Output 10	x9843	x9875	x9930	x9962
Analog Output 11	x9845	x9877	x9931	x9963
Analog Output 12	x9847	x9879	x9932	x9964
Analog Output 13	x9849	x9881	x9933	x9965
Analog Output 14	x9851	x9883	x9934	x9966
Analog Output 15	x9853	x9885	x9935	x9967
Analog Output 16	x9855	x9887	x9936	x9968

5.3.9.6 Alternate Control Output Address Map

Object	Output State	Percent Output	Time On	Status	Alarm Bitfield
Data Encoding	Boolean	32-Bit Float	32-Bit Integer	16-Bit Status	16-Bit Bitfield
Permissions	Read	Read	Read	Read	Read
Control Modes	All except Percent Outputs	Only Percent Outputs	All	All	All
Value	0 = Off 1 = On	%	Seconds	See 5.4 Status Register Codes	See 5.5.6 Relay Alarm Bitfield
Control Output Number	Address	Address	Address	Address	Address
Control Output 1	x9889	x9569	x9969	x9905	x9937
Control Output 2	x9890	x9571	x9971	x9906	x9938
Control Output 3	x9891	x9573	x9973	x9907	x9939
Control Output 4	x9892	x9575	x9975	x9908	x9940
Control Output 5	x9893	x9577	x9977	x9909	x9941
Control Output 6	x9894	x9579	x9979	x9910	x9942
Control Output 7	x9895	x9581	x9981	x9911	x9943
Control Output 8	x9896	x9583	x9983	x9912	x9944
Control Output 9	x9897	x9585	x9985	x9913	x9945
Control Output 10	x9898	x9587	x9987	x9914	x9946
Control Output 11	x9899	x9589	x9989	x9915	x9947
Control Output 12	x9900	x9591	x9991	x9916	x9948
Control Output 13	x9901	x9593	x9993	x9917	x9949
Control Output 14	x9902	x9595	x9995	x9918	x9950
Control Output 15	x9903	x9597	x9997	x9919	x9951
Control Output 16	x9904	x9599	x9999	x9920	x9952

5.4 Status Register Codes

Status Code	Name	Description
0	Error	Generic Error.
1	None	No status to report.
2	Sensor: Auto Cal	Sensor Circuit Auto-Calibration in progress.
3	Sensor: User Cal	Sensor User-Calibration in progress.
4	DI State: Open	DI State is open.
5	DI State: Closed	DI State is closed.
6	DI Interlock: Active	DI Interlock State is active
7	DI Interlock: Inactive	DI Interlock State is inactive
8	Relay: On	Relay is energized.
9	Relay: Off	Relay is not energized.
10	Unused	Unused.
11	Output Interlocked	Output is interlocked by a DI or another output.
12	Output Forced On	Output is forced on by a DI or by another output.
13	Output Timeout	Output timeout limit exceeded.
14	Output Input Error	No valid measurement could be retrieved from the input.
15	Output Error	Error occurred attempting to set the output.
16	Output Hold	Output control on hold due to calibration.
17	Output HOA: Auto On	Output control in Auto Mode, output on.
18	Output HOA: Auto Off	Output control in Auto Mode, output off.
19	Output HOA: Hand	Output control in Hand Mode.
20	Output HOA: Off	Output control in Off Mode.
21	Output Deadband	Output is on and within the deadband area.
22	Relay Timeout	Timeout alarm: output off.
23	Relay OK	Relay reports it is on.
24	Daily Max Timeout	Daily maximum feed time limit exceeded.
25	Biocide: Prebleed	Pre-Bleed active before timed biocide feed.
26	Biocide: Hold	Bio feed bleed lockout in progress.
27	Biocide: Add	Bio feed in progress.
28	Time Proportional: Off	Off period within a time proportional cycle.
29	Bleed & Feed: Bleeding	Bleed valve activated, feed time accumulating.
30	Bleed & Feed: Timeout	Feed time exceeding user-entered feed time limit.
31	Intermittent Sampling: Wait	Wait cycle between readings.
32	Intermittent Sampling: Sample	Sample cycle before new reading.
33	Intermittent Sampling: Hold	Hold cycle before new reading.
34	Intermittent Sampling: Bleed	Bleed cycle after reading.
35	Probe Wash: On	Probe Wash in progress.
36	Probe Wash: Hold	Hold Cycle after probe wash.
37	Unused	Unused.
38	Unused	Unused.
39	Unused	Unused.

Status Code	Name	Description
40	Network: Off-Line	Network connection status disabled.
41	N/A	Requested information is undefined in the current context.
42	LiveConnect: Success	Fluent LiveConnect available
43	LiveConnect: Failure	Fluent LiveConnect unavailable
44	Sensor: Input Failure	Sensor input failure or sensor board alarm.
45	Sensor: Fault Error	Sensor value outside of fault limits.
46	Sensor: Range Alarm	Sensor value outside of range limits.
47	Relay: Cycle Delay	Relay state change delayed by minimum cycle time setting.
48	Sensor: Normal	Sensor is running in normal operation.
49	Sensor: Initializing	Sensor input is initializing.
50	Sensor: Default Temp	Sensor using default temperature instead of sensor value.
51	Alarm Relay: Open	Alarm Output relay closes on an alarm.
52	Alarm Relay: Closed	Alarm Output relay opens on an alarm.
53	Probe Wash: Relay Off	Probe Wash in progress for input sensor.
54	Disabled	Feature is disabled.
55	Duty Cycle: Off	Relay is off due to duty cycle settings.
56	VI Calculation: Error	Calculation error while evaluating a virtual input.
57	Output: On Delay	Relay is off waiting for on delay to expire.
58	Output: Off Delay	Relay is on waiting for off delay to expire.
59	DI Flow Verify: Off	DI Flow Monitor reports an error, output is forced off.
60	DI Flow Verify: Auto	DI Flow Monitor reports an error, output is in auto mode.
61	Output PID Saturated: High	PID integral hold due to output saturated at 100%.
62	Output PID Saturated: Low	PID integral hold due to output saturated at 0%.
63	Output: Lead Lag	Lag is controlling (or being controlled) in automatic mode.
64	DI Flow Verify: Reprime	DI Flow Monitor reports an error, output is forced on.
65	Spike: Onset	Spike onset climb active before reaching spike setpoint.
66	Spike Event: On	Spike onset value achieved, event in progress, output on.
67	Spike Event: Off	Spike onset value achieved, event in progress, output off.
68	Sensor: Stabilizing	Sensor input is in a stabilization delay.
69	Corrosion Sensor: Circuit Test	Corrosion Sensor circuit self-test in progress.
70	Corrosion Sensor: Cable Test	Corrosion Sensor cable test in progress.
71	Corrosion Sensor: Circuit Cal	Corrosion Sensor circuit calibration in progress.
72	Corrosion Sensor: Polarization	Corrosion Sensor polarization measurement in progress.
73	Corrosion Sensor: Imbalance	Corrosion Sensor imbalance measurement in progress.
74	Corrosion Sensor: Resistance	Corrosion Sensor solution resistance measurement.

Status Code	Name	Description
75	Ethernet: Enabled	Ethernet or WiFi communications enabled.
76	WiFi: Invalid Config	WiFi infrastructure mode configuration settings invalid.
77	WiFi: Connecting	WiFi infrastructure mode connection in progress.
78	WiFi: Network Not Found	WiFi infrastructure network not available.
79	WiFi: Invalid Key	WiFi security key for infrastructure network invalid.
80	WiFi: Unable To Connect	WiFi unable to connect to infrastructure network.
81	WiFi: Connected	WiFi infrastructure mode network connection successful.
82	WiFi: Ad-Hoc Mode	WiFi ad-hoc access point is available.
83	Unused	Unused.
84	WiFi: Invalid Config	WiFi ad-hoc mode configuration settings invalid.
85	WiFi: WPA Personal	WiFi security mode WPA Personal (PSK).
86	Unused	Unused.
87	WiFi: WPA2 Personal	WiFi security mode WPA2 Personal (PSK).
88	Unused	Unused.
89	WiFi: WEP	WiFi security mode WEP.
90	Input: Alarm Suppressed	Alarm is suppressed due to selected DI or output condition.
91	Corrosion Sensor: Dry	Corrosion Sensor not submerged in water.
92	Data Logging: Suppressed	Data Logging is suppressed due to selected condition.
93	Webserver: HTTP	Webserver mode HTTP.
94	WS: HTTPS/Default Certificate	Webserver mode HTTPS with default, self-signed certificate
95	WS: HTTPS/User Certificate	Webserver mode HTTPS with user-supplied certificate.

5.5 Alarm Bitfields

Alarm bitfields are comprised of an 8-bit field encapsulated in a 16-bit word. Bit 1 is the least significant bit, bit 8 is the most significant bit. See [4.4.2.2 16-Bit Word \(Bitfield\)](#) for details. Some alarms have multiple causes, consult the Controller Instruction Manual for a comprehensive list of possible alarm causes.

5.5.1 System Alarm Bitfield

System Alarm Bitfield		
Bit Name	Bit No.	Description
Temperature Alarm	1	Controller internal temperatures fall below -10°C or exceed 75°C.
Battery Low	2	The button-cell battery voltage falls below 2.4VDC.
Invalid Setting	3	A hardware change creates invalid settings.
Software Version	4	The firmware of an add-on card needs to be updated.
Board Failure	5	An internal controller component has failed.
Internal Voltage	6	One or more internal (3.3V, 5V, 12V) voltage signal is out of range.
Unused	7	
Unused	8	

5.5.2 Network Alarm Bitfield

Network Alarm Bitfield		
Bit Name	Bit No.	Description
Web Server Failure	1	Internal error when the web server on the Ethernet card fails.
Fluent Data Comm	2	Controller cannot send data to Fluent.
Fluent LiveConnect	3	Controller cannot create a VPN connection to the Fluent server.
WiFi Error	4	Unable to connect to (or create) WiFi network.
Unused	5	
Unused	6	
Unused	7	
Unused	8	

5.5.3 Sensor Input Alarm Bitfield

Sensor Input Alarm Bitfield			
Bit Name	Bit No.	Description	SI Types
Low	1	The sensor reading drops below the Low Alarm setpoint.	All sensor types
High	2	The sensor reading rises above the High Alarm setpoint.	All sensor types
Low Low	3	The sensor reading drops below the Low Low Alarm setpoint.	All sensor types
High High	4	The sensor reading rises above the High High Alarm setpoint.	All sensor types
Replace Electrode †	5	Electrode in service longer than alarm time setpoint.	Corrosion sensors only
Total †	5	The flowmeter total exceeds the limit.	AI Flowmeter only
Unused †	6		
Input Failure †	7	The sensor reading is invalid (out of range, sensor fault, wiring incorrect, sample error, or I/O card failure). This alarm will stop the control for any output using the sensor.	All sensor types
Calibration Required	8	The sensor requires calibration.	All sensor types

† Compatibility Note: In controller software versions 3.09 and earlier, Bit 5 was used for “Out of Range” errors and Bit 6 was used for “Sensor Fault” alarms. In software versions 3.11 and later, these alarms are combined with other types of sensor “Input Failures” reported using Bit 7.

5.5.4 Digital Input Alarm Bitfield

Digital Input Alarm Bitfield			
Bit Name	Bit No.	Description	DI Types
DI State	1	The input is in the state selected to generate an alarm.	DI State & Remote Modbus only
Total	2	The meter total exceeds the limit.	All Digital Meters
Total Range	3	The range of the totalizer is exceeded.	
Input Failure	4	This digital input circuit is no longer functioning.	All DI Types
Flow Verify	5	Feed Monitor unable to verify chemical feed.	Flow Monitor only
Modbus Alarm	5	Modbus message error or update timeout.	Remote Modbus only
Low	6	Flowrate below the Low Alarm setpoint.	Paddlewheel & DI Counter only
High	7	Flowrate above the High Alarm setpoint.	
Unused	8		

5.5.5 Virtual Input Alarm Bitfield

Virtual Input Alarm Bitfield			
Bit Name	Bit No.	Description	VI Types
Low	1	The value drops below the Low Alarm setpoint.	Calculation, Raw Value & Remote Modbus only
High	2	The value rises above the High Alarm setpoint.	
Low Low	3	The value drops below the Low Low Alarm setpoint.	
High High	4	The value rises above the High High Alarm setpoint.	
Out of Range	5	The value is outside of the acceptable range. This alarm will stop the control for any output using the sensor.	Calculation & Remote Modbus only
Deviation	5	The difference between the two inputs exceeds the Deviation Alarm setpoint.	Redundant only
Modbus Alarm	6	Modbus message error or update timeout.	Remote Modbus only
Unused	7		
Input Failure	8	A value required for a virtual calculation is not available. This alarm will stop the control for any output using the sensor.	All VI Types

5.5.6 Relay & Control Output Alarm Bitfield

Relay & Control Output Alarm Bitfield			
Bit Name	Bit No.	Description	Control Modes
Output Timeout	1	The output has been activated for longer than the configured time limit. Control is stopped while the alarm is active.	All modes with <i>Output Time Limit</i> setting
Relay Event Skipped	2	A timer event was not able to be initiated.	All modes with <i>Event Timer settings</i>
Turnover Limit	2	Number of Turns exceeds Turnover Limit setpoint.	Plating Control mode only
Control Failure	3	The output control circuit is no longer functioning.	All Control Modes
State Alarm	4	The output is in the state selected to generate an alarm.	Boolean Logic mode only
Daily Max Timeout	5	The output has been activated during the current day for longer than the configured daily time limit. Control is stopped while the alarm is active.	All modes with <i>Daily Max Time</i> setting
Unused	6		
Unused	7		
Unused	8		

5.5.7 Analog Output Alarm Bitfield

Analog Output Alarm Bitfield			
Bit Name	Bit No.	Description	Control Modes
Output Timeout	1	The output has been activated for longer than the configured time limit. Control is stopped while the alarm is active.	All modes with <i>Output Time Limit</i> setting
Control Failure	2	The analog control circuit is no longer functioning.	All Control Modes
Unused	3		
Unused	4		
Unused	5		
Unused	6		
Unused	7		
Unused	8		